



a  MICROCHIP company

Total Ionizing Dose Test Report

No. 20T-RT4G150-LG1657-K96W1

November 5, 2020

Table of Contents

I. Summary Table.....	3
II. Total Ionizing Dose (TID) Testing.....	3
A. Device-Under-Test (DUT) and Irradiation Parameters	3
B. Test Method.....	4
C. Design and Parametric Measurements.....	4
III. Test Results.....	5
A. Functionality.....	5
B. Power Supply Current.....	5
C. Single-Ended Input Logic Threshold (VIL/VIH).....	19
D. Output-Drive Voltage (VOL/VOH).....	19
E. Propagation Delay.....	28
F. Transition Time	28

I. SUMMARY TABLE

Table. 1. Summary

Parameter	Tolerance
1. Gross Functionality	Passed 125 krad(SiO ₂)
2. Power Supply Current	Passed 125 krad(SiO ₂)
3. Input Threshold (VIL/VIH)	Passed 125 krad(SiO ₂)
4. Output Drive (VOL/VOH)	Passed 125 krad(SiO ₂)
5. Propagation Delay	Passed 125 krad(SiO ₂) for 10% degradation criterion
6. Transition Time	Passed 125 krad(SiO ₂)

II. TOTAL IONIZING DOSE (TID) TESTING

This testing is designed on the basis of an extensive database of TID testing for Radiation-Tolerant FPGAs including flash-based FPGAs. Microsemi TID reports can be found at <http://www.microsemi.com/products/fpga-soc/radtolerant-fpgas/military-aerospace-radiation-reliability-data#tid-reports>

Electrical parameters are measured pre-irradiation and post-irradiation using the burn in design and the Automatic Test Equipment (ATE) program. The report summarizes sample pins.

A. Device-Under-Test (DUT) and Irradiation Parameters

Table 2 lists the DUT and irradiation parameters.

Table. 2. DUT and Irradiation Parameters

Part Number	RT4G150
Package	LG1657
Foundry	United Microelectronics Corp.
Technology	65 nm
DUT Design	Burn in design with inverter string
Die Lot Number	K96W1
Quantity Tested	6
Serial Number (Dose)	03972 (125 krad), 03998 (125 krad), 04002 (125 krad), 04009 (125 krad), 04017 (125 krad), 04037 (125 krad)
Radiation Facility	Defense Microelectronics Activity
Radiation Source	Co-60
Dose Rate	5 krad (SiO ₂)/min
Irradiation Temperature	Room
Irradiation and Measurement Bias	Static at 1.2V/2.5V/3.3V/3.3V
IO Configuration	Single ended Differential Pair

B. Test Method




Fig. 1. Parametric test flow chart

The test method generally follows the guidelines in the military standard TM1019. Figure 1 shows the flow chart describing the steps for the functional and parametric tests.

C. Design and Parametric Measurements

RTG4 FPGA devices have different types of I/Os, such as MSIO and MSIOD, double data rate I/Os (DDRIO), and dedicated I/Os based on functional usage. For more information on I/O naming conventions and I/O description, refer to the RTG4 FPGA Pin Description. All I/Os are tested pre and post-irradiation.

Fabric functionality coverage performed by the burn in design is summarized in table 3 below. In addition to the fabric coverage the supplemental test of propagation delay is also used to determine DUT functionality. These tests are performed pre and post-irradiation and recorded as a pass/fail.

Refer to appendix A for a graphical representation of fabric functional coverage blocks used to perform the functional tests.

Table. 3. Fabric Functional Coverage

Block	Coverage
Combo Block	combinatorial macros available in the RTG4 library
Register Block	sequential macros available in the RTG4 library
UPROM	Maximum output toggle rate(checker board) compared to reference
Embedded SRAM Blocks	full toggle coverage on 209 fabric LSRAM & 210 µRAM blocks using dual port/ two port configurations (x18 width)
Shift Register Block	core utilization
I/O Block	I/O utilization
Math Block	full toggle coverage on 462 fabric math blocks with maximum width configuration

The core power supply current IDD, the I/Os power supply currents (IDDI_2.5/IDDI_3.3) and the charge pump and PLL power supply current (IPP_PLL) are also monitored during irradiation in real time.

The input logic threshold (VIL/VIH) is measured on all single-ended inputs as well as all differential inputs, and is reported as a pass or fail, as part of the ATE test program. The output-drive voltage (VOL/VOH) is also measured on all pins on the MSIO MSIOD and DDRIO. This report contains the output-drive voltage measurements on selected IO pins used in the burn in design. LVTTL and LVCMOS 2.5V standard at different sourcing and sinking currents are reported.

A 2000 stage inverter string is used to measure the propagation delay. The propagation delay is defined as the time delay from the triggering edge at the Clock input to the switching edge at the output. The propagation delay is monitored real time during irradiation and the time difference between positive switching edges of the clock and output are reported. Additionally, the transition characteristics (rise and fall) at the output of the inverter chain are measured pre and post-irradiation. Oscilloscope screen captures are shown in section III. F.

III. TEST RESULTS

A. Functionality

Every DUT passed the pre-irradiation and post-irradiation functional tests mentioned in section II.C.

B. Power Supply Current

The core power supply current (IDD) is 1.2 V, the I/O bank power supply currents (IDDI) are 2.5 V (IDDI_2.5) and 3.3 V (IDDI_3.3). The charge pump and PLL power supply current (IPP_PLL) is 3.3 V. Figures 2-25 illustrate the plot of in-flux standby IDD, IDDI_2.5, IDDI_3.3 and IPP_PLL versus total dose for every DUT. Tables 4-7 summarize the pre-irradiation and post-irradiation total current (static & dynamic) IDD, IDDI_2.5, IDDI_3.3 and IPP_PLL.

Table. 4. Pre-irradiation and Post-irradiation I_{DD}

DUT	Total Dose	Pre-irradiation (A)	Post-irradiation (A)	Increase (%)
03972	125 krad	0.3853	0.4009	4.05
03998	125 krad	0.3844	0.3990	3.80
04002	125 krad	0.4444	0.4610	3.74
04009	125 krad	0.4428	0.4620	4.34
04017	125 krad	0.4100	0.4280	4.39
04037	125 krad	0.4368	0.4498	2.98

Table. 5. Pre-irradiation and Post-irradiation $I_{DDI_2.5}$

DUT	Total Dose	Pre-irradiation (A)	Post-irradiation (A)	Increase (%)
03972	125 krad	0.0089	0.0107	20.22
03998	125 krad	0.0089	0.0106	19.10
04002	125 krad	0.0096	0.0111	15.63
04009	125 krad	0.0101	0.0120	18.81
04017	125 krad	0.0091	0.0107	17.58
04037	125 krad	0.0091	0.0103	13.19

Table. 6. Pre-irradiation and Post-irradiation $I_{DDI_3.3}$

DUT	Total Dose	Pre-irradiation (A)	Post-irradiation (A)	Increase (%)
03972	125 krad	0.0334	0.0362	8.38
03998	125 krad	0.0332	0.0361	8.73
04002	125 krad	0.0334	0.0363	8.68
04009	125 krad	0.0339	0.0367	8.26
04017	125 krad	0.0328	0.0355	8.23
04037	125 krad	0.0333	0.0359	7.81

Table. 7. Pre-irradiation and Post-irradiation I_{PP_PLL}

DUT	Total Dose	Pre-irradiation (A)	Post-irradiation (A)	Increase (%)
03972	125 krad	0.0154	0.0166	7.79
03998	125 krad	0.0154	0.0161	4.55
04002	125 krad	0.0153	0.0192	25.49
04009	125 krad	0.0152	0.0186	22.37
04017	125 krad	0.0152	0.0195	28.29
04037	125 krad	0.0152	0.0165	8.55

The following figures (2-25) show the in-beam monitoring of the currents mentioned above as a function of TID for the available DUTs.




Fig. 2. DUT 3972 core power supply current (I_{DD}) versus TID




Fig. 3. DUT 3998 core power supply current (I_{DD}) versus TID




Fig. 4. DUT 4002 core power supply current (I_{DD}) versus TID




Fig. 5. DUT 4009 core power supply current (I_{DD}) versus TID




Fig. 6. DUT 4017 core power supply current (I_{DD}) versus TID




Fig. 7. DUT 4037 core power supply current (I_{DD}) versus TID




Fig. 8. DUT 3972 I/O bank 2.5V power supply current ($I_{DDI_2.5}$) versus TID




Fig. 9. DUT 3998 I/O bank 2.5V power supply current ($I_{DDI_2.5}$) versus TID




Fig. 10. DUT 4002 I/O bank 2.5V power supply current ($I_{DDI_2.5}$) versus TID




Fig. 11. DUT 4009 I/O bank 2.5V power supply current ($I_{DDI_2.5}$) versus TID




Fig. 12. DUT 4017 I/O bank 2.5V power supply current ($I_{DDI_2.5}$) versus TID




Fig. 13. DUT 4037 I/O bank 2.5V power supply current ($I_{DDI_2.5}$) versus TID




Fig. 14. DUT 3972 I/O bank 3.3V power supply current ($I_{DDI_3.3}$) versus TID




Fig. 15. DUT 3998 I/O bank 3.3V power supply current ($I_{DDI_3.3}$) versus TID




Fig. 16. DUT 4002 I/O bank 3.3V power supply current ($I_{DDI_3.3}$) versus TID




Fig. 17. DUT 4009 I/O bank 3.3V power supply current ($I_{DDI_3.3}$) versus TID




Fig. 18. DUT 4017 I/O bank 3.3V power supply current ($I_{DDI_3.3}$) versus TID




Fig. 19. DUT 4037 I/O bank 3.3V power supply current ($I_{DDI_3.3}$) versus TID




Fig. 20. DUT 3972 charge pump and PLL power supply current (I_{PP_PLL}) versus TID




Fig. 21. DUT 3998 charge pump and PLL power supply current (I_{PP_PLL}) versus TID




Fig. 22. DUT 4002 charge pump and PLL power supply current (I_{PP_PLL}) versus TID




Fig. 23. DUT 4009 charge pump and PLL power supply current (I_{PP_PLL}) versus TID




Fig. 24. DUT 4017 charge pump and PLL power supply current (I_{PP_PLL}) versus TID




Fig. 25. DUT 4037 charge pump and PLL power supply current (I_{PP_PLL}) versus TID

C. Single-Ended Input Logic Threshold (VIL/VIH)

The input switching threshold, or trip point, is defined as the applied input voltage at which the output of the design starts to switch. VIH is the input trip point when the input is going high to low and VIL is the input trip point when the input is going low to high. The input logic threshold (VIL/VIH) is measured on all single-ended inputs as well as all differential input and recorded as pass or fail. All I/Os are tested at their respective I/O standards and are compliant to the JEDEC specs. Refer to http://www.microsemi.com/document-portal/doc_view/135193-ds0131-rtg4-fpga-datasheet for more information.

The 3 DUTs tested passed with respect to the testing specification pre and post-irradiation. This pass/fail is determined as part of the ATE test program used to perform pre and post-irradiation electrical parametric measurements.

Table. 8. VIH Summary

DUT	Pre-irradiation	Post-irradiation
03972	Passed	Passed
03998	Passed	Passed
04002	Passed	Passed
04009	Passed	Passed
04017	Passed	Passed
04037	Passed	Passed

Table. 9. VIL Summary

DUT	Pre-irradiation	Post-irradiation
03972	Passed	Passed
03998	Passed	Passed
04002	Passed	Passed
04009	Passed	Passed
04017	Passed	Passed
04037	Passed	Passed

D. Output-Drive Voltage (VOL/VOH)

The pre-irradiation and post-irradiation output-drive voltages (VOL/VOH) are performed on all available IOs. The measurements performed pre and post irradiation are within the specification limits; in each case, the radiation-induced degradation is within 10%. For the purpose of this report, the measurements presented below in tables 10 through 33 are sampled on several pins used in the burn in design.

Table. 10. LVC MOS 25 VOH – DUT 03972

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID BUF OUT	A33	2.134	2.135	2.203	2.203	2.175	2.152
EPCSRST_N_0	B31	2.135	2.135	2.203	2.203	2.175	2.155
EPCSRST_N_1	B32	2.136	2.136	2.205	2.205	2.177	2.154
EPCSRST_N_2	B34	2.135	2.135	2.204	2.204	2.175	2.155
EPCSRST_N_3	B35	2.136	2.136	2.205	2.205	2.178	2.158
EPCSRST_N_4	B36	2.134	2.134	2.202	2.202	2.173	2.152
EPCSRST_N_5	B37	2.135	2.135	2.204	2.204	2.176	2.155
MONITOR	K23	2.135	2.134	2.204	2.204	2.176	2.156
PLL MON	L20	2.136	2.136	2.207	2.206	2.180	2.162
TOGGLE MON	L22	2.135	2.134	2.206	2.205	2.179	2.178

Table. 11. LVC MOS 25 VOH – DUT 03998

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID BUF OUT	A33	2.135	2.132	2.203	2.203	2.175	2.155
EPCSRST_N_0	B31	2.136	2.131	2.204	2.208	2.175	2.174
EPCSRST_N_1	B32	2.137	2.136	2.205	2.205	2.178	2.177
EPCSRST_N_2	B34	2.135	2.135	2.204	2.203	2.175	2.175
EPCSRST_N_3	B35	2.136	2.136	2.206	2.206	2.179	2.178
EPCSRST_N_4	B36	2.135	2.134	2.203	2.203	2.175	2.174
EPCSRST_N_5	B37	2.136	2.136	2.204	2.204	2.176	2.176
MONITOR	K23	2.136	2.135	2.205	2.204	2.177	2.176
PLL MON	L20	2.136	2.135	2.207	2.206	2.180	2.179
TOGGLE MON	L22	2.136	2.136	2.207	2.206	2.180	2.179

Table. 12. LVC MOS 25 VOH – DUT 04002

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID BUF OUT	A33	2.134	2.134	2.203	2.202	2.174	2.174
EPCSRST_N_0	B31	2.136	2.136	2.203	2.203	2.175	2.174
EPCSRST_N_1	B32	2.136	2.136	2.205	2.205	2.177	2.176
EPCSRST_N_2	B34	2.135	2.135	2.203	2.203	2.175	2.175
EPCSRST_N_3	B35	2.136	2.135	2.205	2.205	2.178	2.178
EPCSRST_N_4	B36	2.134	2.134	2.203	2.203	2.175	2.174
EPCSRST_N_5	B37	2.135	2.135	2.204	2.204	2.176	2.175
MONITOR	K23	2.134	2.134	2.204	2.204	2.176	2.157
PLL MON	L20	2.136	2.136	2.207	2.206	2.180	2.179
TOGGLE MON	L22	2.136	2.135	2.206	2.205	2.179	2.179

Table. 13. LVC MOS 25 VOH – DUT 04009

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID_BUF_OUT	A33	2.133	2.133	2.202	2.202	2.173	2.173
EPCSRST_N_0	B31	2.134	2.133	2.203	2.203	2.174	2.174
EPCSRST_N_1	B32	2.135	2.134	2.204	2.204	2.177	2.176
EPCSRST_N_2	B34	2.133	2.133	2.202	2.202	2.174	2.173
EPCSRST_N_3	B35	2.135	2.134	2.204	2.204	2.177	2.176
EPCSRST_N_4	B36	2.133	2.132	2.202	2.201	2.173	2.172
EPCSRST_N_5	B37	2.133	2.133	2.203	2.203	2.175	2.174
MONITOR	K23	2.133	2.132	2.203	2.203	2.175	2.155
PLL_MON	L20	2.135	2.134	2.206	2.205	2.179	2.179
TOGGLE_MON	L22	2.135	2.133	2.205	2.204	2.178	2.177

Table. 14. LVC MOS 25 VOH – DUT 04017

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID BUF OUT	A33	2.133	2.132	2.202	2.202	2.173	2.174
EPCSRST_N_0	B31	2.135	2.134	2.203	2.203	2.175	2.174
EPCSRST_N_1	B32	2.135	2.134	2.204	2.204	2.177	2.176
EPCSRST_N_2	B34	2.134	2.134	2.203	2.203	2.175	2.175
EPCSRST_N_3	B35	2.135	2.135	2.204	2.204	2.177	2.177
EPCSRST_N_4	B36	2.133	2.133	2.202	2.201	2.173	2.172
EPCSRST_N_5	B37	2.134	2.134	2.204	2.203	2.175	2.175
MONITOR	K23	2.134	2.133	2.203	2.203	2.175	2.175
PLL_MON	L20	2.135	2.134	2.206	2.205	2.179	2.179
TOGGLE_MON	L22	2.135	2.134	2.205	2.204	2.178	2.177

Table. 15. LVC MOS 25 VOH – DUT 04037

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID_BUF_OUT	A33	2.135	2.135	2.203	2.204	2.175	2.175
EPCSRST_N_0	B31	2.136	2.135	2.204	2.204	2.176	2.175
EPCSRST_N_1	B32	2.137	2.136	2.206	2.205	2.178	2.178
EPCSRST_N_2	B34	2.136	2.135	2.204	2.204	2.175	2.175
EPCSRST_N_3	B35	2.137	2.137	2.206	2.206	2.179	2.179
EPCSRST_N_4	B36	2.136	2.135	2.204	2.203	2.175	2.175
EPCSRST_N_5	B37	2.136	2.135	2.204	2.204	2.176	2.176
MONITOR	K23	2.136	2.135	2.205	2.204	2.177	2.176
PLL_MON	L20	2.137	2.136	2.207	2.207	2.181	2.180
TOGGLE_MON	L22	2.137	2.136	2.207	2.206	2.180	2.179

Table. 16. LVC MOS 25 VOL – DUT 03972

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID_BUF_OUT	A33	235.2	233.1	167.6	164.4	195.5	193.5
EPCSRST_N_0	B31	234.4	233.6	167.5	166.5	195.6	191.8
EPCSRST_N_1	B32	233.2	232.6	165.5	165.4	192.7	192.6
EPCSRST_N_2	B34	234.9	234.1	167.4	166.8	195.2	194.4
EPCSRST_N_3	B35	234.8	233.8	166.1	165.5	193.1	192.2
EPCSRST_N_4	B36	236.3	235.6	169.1	168.8	197.4	197.2
EPCSRST_N_5	B37	235.4	234.5	167.4	166.6	195.1	194.2
MONITOR	K23	233.8	233.1	165.9	165.6	193.0	192.8
PLL_MON	L20	232.7	231.8	163.4	163.1	189.5	189.0
TOGGLE_MON	L22	233.2	232.7	164.0	164.1	190.2	190.5

Table. 17. LVC MOS 25 VOL – DUT 03998

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID BUF OUT	A33	235.2	235.3	168.1	166.9	196.2	195.0
EPCSRST_N_0	B31	234.4	236.0	167.0	172.3	194.8	196.8
EPCSRST_N_1	B32	233.3	232.9	165.4	165.4	192.5	192.8
EPCSRST_N_2	B34	235.2	234.6	167.7	167.3	195.6	195.0
EPCSRST_N_3	B35	234.6	233.8	165.7	165.2	192.6	191.9
EPCSRST_N_4	B36	236.0	235.5	168.1	168.0	196.2	196.3
EPCSRST_N_5	B37	235.0	234.1	167.3	166.6	195.0	194.3
MONITOR	K23	233.8	233.3	165.8	165.5	192.9	192.7
PLL_MON	L20	232.7	232.2	163.2	163.1	189.3	189.2
TOGGLE_MON	L22	232.6	232.1	163.5	163.6	189.6	189.9

Table. 18. LVC MOS 25 VOL – DUT 04002

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID_BUF_OUT	A33	235.8	235.2	167.8	167.2	196.2	195.1
EPCSRST_N_0	B31	233.7	236.8	166.7	171.2	195.3	200.3
EPCSRST_N_1	B32	233.5	233.2	165.5	165.5	192.6	192.8
EPCSRST_N_2	B34	235.1	234.7	167.4	167.1	195.4	195.0
EPCSRST_N_3	B35	234.7	234.1	165.7	165.3	192.7	192.3
EPCSRST_N_4	B36	236.0	235.7	168.1	168.1	196.1	196.2
EPCSRST_N_5	B37	235.5	234.9	167.2	166.8	194.9	194.4
MONITOR	K23	234.5	234.1	166.2	166.2	193.4	193.4
PLL_MON	L20	232.3	231.9	163.1	162.7	189.2	188.8
TOGGLE_MON	L22	232.7	232.4	163.5	163.7	189.7	190.2

Table. 19. LVC MOS 25 VOL – DUT 04009

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID_BUF_OUT	A33	237.7	236.9	169.6	168.7	197.7	196.6
EPCSRST_N_0	B31	236.8	236.3	169.0	168.3	197.1	196.7
EPCSRST_N_1	B32	235.5	235.3	166.9	167.0	194.2	194.5
EPCSRST_N_2	B34	237.4	237.2	169.2	168.9	197.2	197.1
EPCSRST_N_3	B35	236.5	236.0	167.2	166.9	194.4	194.0
EPCSRST_N_4	B36	238.4	238.2	169.6	170.1	198.0	198.6
EPCSRST_N_5	B37	237.7	237.3	168.7	168.3	196.7	196.2
MONITOR	K23	236.8	236.3	167.8	167.5	195.2	195.0
PLL_MON	L20	234.8	234.4	164.7	164.5	190.9	190.7
TOGGLE_MON	L22	234.8	234.7	165.2	165.3	191.6	191.8
						219.3	250.2
						219.3	251.7
						219.3	263.7
						219.3	265.5
						219.3	266.2
						219.3	267.0
						219.3	268.4
						219.3	269.9
						219.3	270.3
						219.3	273.3
						219.3	275.5
						219.3	275.8
						219.3	276.1
						219.3	276.4
						219.3	276.7
						219.3	277.8
						219.3	278.7
						219.3	279.9
						219.3	280.7
						219.3	280.7

Table. 20. LVC MOS 25 VOL – DUT 04017

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID BUF OUT	A33	237.2	236.4	168.8	167.8	196.6	195.7
EPCSRST_N_0	B31	235.5	235.2	167.8	167.7	196.6	195.7
EPCSRST_N_1	B32	234.7	234.4	166.2	166.2	193.4	193.4
EPCSRST_N_2	B34	236.5	235.9	168.1	167.7	195.9	195.4
EPCSRST_N_3	B35	236.1	235.3	167.0	166.5	194.2	193.6
EPCSRST_N_4	B36	237.4	236.9	169.7	169.6	198.2	198.3
EPCSRST_N_5	B37	236.9	236.2	168.2	167.5	195.9	195.2
MONITOR	K23	235.2	234.6	166.8	166.6	194.2	194.1
PLL_MON	L20	233.7	233.1	164.2	163.8	190.4	190.0
TOGGLE_MON	L22	233.8	233.2	164.6	164.7	191.0	191.2
						219.3	251.7
						219.3	252.1
						219.3	265.6
						219.3	266.2
						219.3	267.0
						219.3	268.4
						219.3	269.9
						219.3	270.3
						219.3	273.3
						219.3	275.5
						219.3	275.8
						219.3	276.1
						219.3	276.4
						219.3	276.7
						219.3	277.8
						219.3	278.7
						219.3	279.9
						219.3	280.7
						219.3	280.7

Table. 21. LVC MOS 25 VOL – DUT 04037

Pin Name	Pin#	2mA	4mA	6mA	8mA	12mA	14mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad	Post-rad
TID_BUF_OUT	A33	234.4	233.0	166.9	166.1	195.4	193.9
EPCSRST_N_0	B31	233.2	232.5	166.5	166.1	193.8	193.6
EPCSRST_N_1	B32	232.0	231.7	164.4	164.6	191.5	191.8
EPCSRST_N_2	B34	234.0	233.5	166.7	166.3	194.6	194.0
EPCSRST_N_3	B35	233.0	232.2	164.8	164.5	191.6	191.3
EPCSRST_N_4	B36	234.1	233.5	167.2	167.1	195.1	195.2
EPCSRST_N_5	B37	234.4	233.5	166.4	165.9	194.0	193.4
MONITOR	K23	232.8	232.2	164.9	164.9	192.0	192.2
PLL_MON	L20	231.4	230.9	162.5	162.2	188.4	188.2
TOGGLE_MON	L22	230.9	230.6	162.8	163.0	188.9	189.2
						207.1	207.5
						207.1	234.7
						207.1	235.6
						207.1	246.4
						207.1	247.5

Table. 22. LVTTL VOH – DUT 03972

Pin Name	Pin#	2mA	4mA	8mA	12mA	16mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad
TID_BUF_OUT	A33	2.922	2.919	2.912	2.914	2.894
EPCSRST_N_0	B31	2.922	2.922	2.913	2.909	2.894
EPCSRST_N_1	B32	2.923	2.923	2.915	2.914	2.897
EPCSRST_N_2	B34	2.923	2.922	2.913	2.913	2.895
EPCSRST_N_3	B35	2.923	2.923	2.915	2.915	2.898
EPCSRST_N_4	B36	2.921	2.921	2.912	2.911	2.892
EPCSRST_N_5	B37	2.923	2.922	2.913	2.913	2.896
MONITOR	K23	2.921	2.921	2.913	2.913	2.896
PLL_MON	L20	2.922	2.922	2.916	2.915	2.901
TOGGLE_MON	L22	2.922	2.921	2.914	2.914	2.900

Table. 23. LVTTL VOH – DUT 03998

Pin Name	Pin#	2mA	4mA	8mA	12mA	16mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad
TID_BUF_OUT	A33	2.922	2.922	2.913	2.913	2.894
EPCSRST_N_0	B31	2.923	2.923	2.913	2.913	2.895
EPCSRST_N_1	B32	2.924	2.923	2.915	2.914	2.898
EPCSRST_N_2	B34	2.922	2.922	2.913	2.913	2.894
EPCSRST_N_3	B35	2.924	2.923	2.915	2.915	2.899
EPCSRST_N_4	B36	2.922	2.922	2.913	2.912	2.894
EPCSRST_N_5	B37	2.923	2.923	2.914	2.914	2.896
MONITOR	K23	2.922	2.922	2.914	2.913	2.897
PLL_MON	L20	2.923	2.922	2.916	2.915	2.901
TOGGLE_MON	L22	2.923	2.922	2.916	2.915	2.901

Table. 24. LVTTL VOH – DUT 04002

Pin Name	Pin#	2mA	4mA	8mA	12mA	16mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad
TID_BUF_OUT	A33	2.922	2.921	2.912	2.913	2.894
EPCSRST_N_0	B31	2.922	2.922	2.913	2.913	2.895
EPCSRST_N_1	B32	2.924	2.923	2.915	2.914	2.898
EPCSRST_N_2	B34	2.922	2.922	2.913	2.913	2.894
EPCSRST_N_3	B35	2.923	2.923	2.915	2.915	2.898
EPCSRST_N_4	B36	2.922	2.921	2.913	2.912	2.894
EPCSRST_N_5	B37	2.922	2.922	2.913	2.913	2.895
MONITOR	K23	2.921	2.921	2.913	2.912	2.896
PLL_MON	L20	2.923	2.923	2.916	2.915	2.901
TOGGLE_MON	L22	2.922	2.922	2.915	2.914	2.900

Table. 25. LVTTL VOH – DUT 04009

Pin Name	Pin#	2mA	4mA	8mA	12mA	16mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad
TID_BUF_OUT	A33	2.920	2.920	2.911	2.911	2.893
EPCSRST_N_0	B31	2.921	2.921	2.911	2.911	2.893
EPCSRST_N_1	B32	2.922	2.922	2.913	2.913	2.897
EPCSRST_N_2	B34	2.921	2.920	2.911	2.911	2.893
EPCSRST_N_3	B35	2.922	2.921	2.914	2.913	2.897
EPCSRST_N_4	B36	2.920	2.919	2.911	2.910	2.892
EPCSRST_N_5	B37	2.921	2.920	2.912	2.912	2.894
MONITOR	K23	2.920	2.920	2.912	2.911	2.895
PLL_MON	L20	2.921	2.921	2.914	2.914	2.900
TOGGLE_MON	L22	2.921	2.920	2.914	2.913	2.899

Table. 26. LVTTL VOH – DUT 04017

Pin Name	Pin#	2mA	4mA	8mA	12mA	16mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad
TID_BUF_OUT	A33	2.920	2.920	2.911	2.912	2.892
EPCSRST_N_0	B31	2.922	2.922	2.912	2.912	2.893
EPCSRST_N_1	B32	2.922	2.922	2.914	2.913	2.897
EPCSRST_N_2	B34	2.922	2.921	2.912	2.912	2.894
EPCSRST_N_3	B35	2.923	2.922	2.914	2.914	2.897
EPCSRST_N_4	B36	2.921	2.920	2.911	2.910	2.892
EPCSRST_N_5	B37	2.922	2.921	2.913	2.913	2.895
MONITOR	K23	2.921	2.920	2.912	2.912	2.895
PLL_MON	L20	2.922	2.922	2.915	2.914	2.900
TOGGLE_MON	L22	2.922	2.921	2.914	2.913	2.899

Table. 27. LVTTL VOH – DUT 04037

Pin Name	Pin#	2mA	4mA	8mA	12mA	16mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad
TID_BUF_OUT	A33	2.923	2.923	2.914	2.914	2.895
EPCSRST_N_0	B31	2.924	2.923	2.914	2.915	2.896
EPCSRST_N_1	B32	2.925	2.924	2.916	2.916	2.899
EPCSRST_N_2	B34	2.923	2.923	2.914	2.914	2.896
EPCSRST_N_3	B35	2.925	2.925	2.916	2.916	2.900
EPCSRST_N_4	B36	2.924	2.923	2.914	2.913	2.895
EPCSRST_N_5	B37	2.924	2.923	2.915	2.915	2.897
MONITOR	K23	2.923	2.922	2.914	2.914	2.898
PLL_MON	L20	2.924	2.924	2.917	2.916	2.903
TOGGLE_MON	L22	2.924	2.924	2.916	2.916	2.901



Total Ionizing Dose Test Report

No. 20T-RT4G150-LG1657-K96W1

Rev. 0

Table. 28. LVTTL VOL – DUT 03972

		2mA		4mA		8mA		12mA		16mA	
Pin Name	Pin#	Pre-rad	Post-rad								
TID_BUF_OUT	A33	215.1	214.9	223.7	222.6	241.9	245.1	260.1	260.4	276.0	271.9
EPCSRST_N_0	B31	214.7	218.5	222.4	240.1	241.0	238.2	260.0	262.6	278.2	268.6
EPCSRST_N_1	B32	213.3	212.9	221.0	220.6	238.3	238.7	255.5	255.9	273.0	273.5
EPCSRST_N_2	B34	214.7	214.1	223.2	222.2	241.5	240.7	259.7	258.5	277.9	276.7
EPCSRST_N_3	B35	214.5	214.0	222.1	220.6	238.5	237.5	255.0	253.8	271.4	270.2
EPCSRST_N_4	B36	216.2	215.6	224.9	224.4	244.3	244.2	263.6	263.9	283.2	283.7
EPCSRST_N_5	B37	215.1	214.3	223.3	222.0	241.5	240.0	259.1	257.8	277.1	275.6
MONITOR	K23	213.6	212.9	221.5	220.9	238.2	238.0	255.1	255.0	272.2	272.1
PLL_MON	L20	212.3	211.9	219.8	219.3	233.3	233.3	247.9	247.5	263.0	262.7
TOGGLE_MON	L22	212.6	212.4	219.2	218.6	234.5	235.0	249.4	250.3	264.5	266.0

Table. 29. LVTTL VOL – DUT 03998

		2mA		4mA		8mA		12mA		16mA	
Pin Name	Pin#	Pre-rad	Post-rad								
TID_BUF_OUT	A33	214.8	214.0	223.7	221.7	242.7	240.6	261.2	258.5	281.1	277.6
EPCSRST_N_0	B31	214.3	213.5	223.5	221.2	241.1	239.6	258.5	258.1	279.5	277.2
EPCSRST_N_1	B32	213.5	213.1	221.2	220.6	238.0	238.4	255.2	255.7	272.2	273.2
EPCSRST_N_2	B34	215.0	214.4	223.5	222.6	242.0	241.6	260.1	259.5	278.6	277.7
EPCSRST_N_3	B35	214.4	213.7	221.6	220.3	237.9	237.3	254.2	253.5	270.9	269.9
EPCSRST_N_4	B36	215.8	215.2	224.4	223.7	242.7	242.8	260.9	261.5	279.8	280.5
EPCSRST_N_5	B37	214.6	213.9	223.3	222.1	241.1	240.0	258.9	257.8	277.0	275.6
MONITOR	K23	213.7	212.9	221.2	220.7	238.1	238.2	255.0	255.1	271.8	272.1
PLL_MON	L20	212.6	212.1	220.0	219.7	233.7	233.5	247.9	247.8	262.8	263.1
TOGGLE_MON	L22	212.0	211.8	218.2	217.9	233.7	234.3	248.2	249.3	263.3	264.6

Table. 30. LVTTL VOL – DUT 04002

		2mA		4mA		8mA		12mA		16mA	
Pin Name	Pin#	Pre-rad	Post-rad								
TID_BUF_OUT	A33	215.4	214.8	223.6	221.5	242.2	240.7	261.0	259.3	280.1	277.5
EPCSRST_N_0	B31	214.2	214.4	222.6	222.1	241.5	239.6	258.9	257.9	279.7	277.4
EPCSRST_N_1	B32	213.6	213.2	221.3	220.9	238.1	238.5	255.4	256.3	272.4	273.6
EPCSRST_N_2	B34	215.1	214.6	223.4	222.4	241.7	241.0	259.8	259.2	278.4	277.6
EPCSRST_N_3	B35	214.6	213.8	221.8	220.8	238.2	237.5	254.2	253.6	270.7	269.9
EPCSRST_N_4	B36	215.7	215.2	223.9	223.5	242.5	242.7	261.2	261.8	280.0	280.8
EPCSRST_N_5	B37	215.3	214.7	223.1	222.3	241.2	240.4	258.8	257.8	276.7	275.5
MONITOR	K23	213.9	213.9	222.1	221.5	238.8	238.8	255.5	255.8	272.5	272.7
PLL_MON	L20	212.1	211.7	219.7	219.1	233.4	232.9	247.6	247.0	262.6	261.9
TOGGLE_MON	L22	212.2	212.0	218.4	218.2	233.8	234.5	248.5	249.4	263.5	264.6

Table. 31. LVTTL VOL – DUT 04009

Pin Name	Pin#	2mA	4mA	8mA	12mA	16mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad
TID_BUF_OUT	A33	217.3	216.1	224.9	224.6	243.1
EPCSRST_N_0	B31	216.6	215.7	225.4	224.2	243.4
EPCSRST_N_1	B32	215.5	215.4	223.0	223.0	240.1
EPCSRST_N_2	B34	217.0	216.7	225.8	225.0	244.2
EPCSRST_N_3	B35	216.1	215.7	223.8	222.7	239.9
EPCSRST_N_4	B36	217.8	217.8	226.4	226.4	244.7
EPCSRST_N_5	B37	217.5	216.8	225.4	224.5	243.3
MONITOR	K23	216.0	215.7	224.1	223.5	240.9
PLL_MON	L20	214.2	214.1	221.7	221.4	235.2
TOGGLE_MON	L22	214.3	214.2	220.8	220.3	236.3

Table. 32. LVTTL VOL – DUT 04017

Pin Name	Pin#	2mA	4mA	8mA	12mA	16mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad
TID_BUF_OUT	A33	216.4	215.5	224.9	224.0	242.7
EPCSRST_N_0	B31	214.8	214.1	223.2	223.0	242.7
EPCSRST_N_1	B32	214.4	214.1	221.7	221.6	238.6
EPCSRST_N_2	B34	215.8	215.1	224.1	223.1	241.9
EPCSRST_N_3	B35	215.4	215.0	223.2	222.1	239.4
EPCSRST_N_4	B36	216.6	216.2	225.8	224.9	245.2
EPCSRST_N_5	B37	216.2	215.6	224.3	223.1	241.9
MONITOR	K23	214.3	213.9	222.4	221.7	239.4
PLL_MON	L20	213.1	212.5	220.6	220.1	234.4
TOGGLE_MON	L22	212.8	212.4	219.7	219.4	235.2

Table. 33. LVTTL VOL – DUT 04037

Pin Name	Pin#	2mA	4mA	8mA	12mA	16mA
		Pre-rad	Post-rad	Pre-rad	Post-rad	Pre-rad
TID_BUF_OUT	A33	213.6	212.9	222.6	221.5	241.3
EPCSRST_N_0	B31	213.2	212.2	220.7	220.9	238.9
EPCSRST_N_1	B32	212.0	211.6	219.5	219.5	236.5
EPCSRST_N_2	B34	213.6	213.0	221.9	221.1	240.1
EPCSRST_N_3	B35	212.5	211.9	220.1	219.3	236.5
EPCSRST_N_4	B36	213.5	213.1	222.3	222.0	240.9
EPCSRST_N_5	B37	213.7	213.2	222.0	220.9	239.6
MONITOR	K23	212.4	211.9	220.2	219.7	237.0
PLL_MON	L20	210.9	210.4	218.0	217.8	232.0
TOGGLE_MON	L22	210.4	210.0	217.1	216.9	232.5

E. Propagation Delay

Table 34 lists the pre-irradiation and post-irradiation propagation delay measurements. It shows that the change due to radiation on each DUT is not significant and every DUT passes the 10% degradation criterion.

Table. 34. Pre-irradiation and Post-irradiation Propagation Delay Change

DUT	Total Dose	Pre-irradiation (μ s)	Post-irradiation (μ s)	Change Degradation (%)
03972	125 krad	0.4448	0.4470	0.49
03998	125 krad	0.4496	0.4532	0.79
04002	125 krad	0.4545	0.4579	0.75
04009	125 krad	0.4549	0.4584	0.77
04017	125 krad	0.4519	0.4532	0.29
04037	125 krad	0.4502	0.4502	0.01

F. Transition Time

The figures below show the pre-irradiation and post-irradiation transitions edges. In each case the radiation induced transition degradation is not observable.




Fig. 26 (a). DUT 3972 pre-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 26 (b). DUT 3972 post-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 27 (a). DUT 3998 pre-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 27 (b). DUT 3998 post-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 28 (a). DUT 4002 pre-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 28 (b). DUT 4002 post-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 29 (a). DUT 4009 pre-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 29 (b). DUT 4009 post-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 30 (a). DUT 4017 pre-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 30 (b). DUT 4017 post-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 31 (a). DUT 4037 pre-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 31 (b). DUT 4037 post-irradiation rising edge, abscissa scale is 1V/div and ordinate scale is 2ns/div



Fig. 32 (a). DUT 3972 pre-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 32 (b). DUT 3972 post-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div



Fig. 33 (a). DUT 3998 pre-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 33 (b). DUT 3998 post-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 34 (a). DUT 4002 pre-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div



Fig. 34 (b). DUT 4002 post-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 35 (a). DUT 4009 pre-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 35 (b). DUT 4009 post-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div



Fig. 36 (a). DUT 4017 pre-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 36 (b). DUT 4017 post-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div



Fig. 37 (a). DUT 4037 pre-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div




Fig. 37 (b). DUT 4037 post-irradiation Falling edge, abscissa scale is 1V/div and ordinate scale is 2ns/div

Appendix A

Table. 35. High level block diagrams of blocks used to perform fabric functional coverage pre and post-irradiation

Block	Coverage
Combo Block	combinatorial macros available in the RTG4 library
Register Block	sequential macros available in the RTG4 library
UPROM	
Embedded SRAM Blocks	full toggle coverage on 209 fabric LSRAM & 210 μ RAM blocks using dual port/ two port configurations (x18 width)
Shift Register Block	core utilization
IO Block	IO utilization
Math Block	full toggle coverage on 462 fabric math blocks with maximum width configuration




Fig. 38. Combo Block




Fig. 39. Shift Register Block




Fig. 40. Embedded Ram Blocks




Fig. 41. IO Block




Fig. 42. Math Block



Microsemi Headquarters
One Enterprise, Aliso Viejo,
CA 92656 USA
Within the USA: +1 (800) 713-4113
Outside the USA: +1 (949) 380-6100
Sales: +1 (949) 380-6136
Fax: +1 (949) 215-4996
Email: AVO-sales.support@microchip.com
www.microsemi.com

© 2015–2018 Microsemi. All rights reserved. Microsemi and the Microsemi logo are trademarks of Microsemi Corporation. All other trademarks and service marks are the property of their respective owners.

Microsemi makes no warranty, representation, or guarantee regarding the information contained herein or the suitability of its products and services for any particular purpose, nor does Microsemi assume any liability whatsoever arising out of the application or use of any product or circuit. The products sold hereunder and any other products sold by Microsemi have been subject to limited testing and should not be used in conjunction with mission-critical equipment or applications. Any performance specifications are believed to be reliable but are not verified, and Buyer must conduct and complete all performance and other testing of the products, alone and together with, or installed in, any end-products. Buyer shall not rely on any data and performance specifications or parameters provided by Microsemi. It is the Buyer's responsibility to independently determine suitability of any products and to test and verify the same. The information provided by Microsemi hereunder is provided "as is, where is" and with all faults, and the entire risk associated with such information is entirely with the Buyer. Microsemi does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other IP rights, whether with regard to such information itself or anything described by such information. Information provided in this document is proprietary to Microsemi, and Microsemi reserves the right to make any changes to the information in this document or to any products and services at any time without notice.

Microsemi, a wholly owned subsidiary of Microchip Technology Inc. (Nasdaq: MCHP), offers a comprehensive portfolio of semiconductor and system solutions for aerospace & defense, communications, data center and industrial markets. Products include high-performance and radiation-hardened analog mixed-signal integrated circuits, FPGAs, SoCs and ASICs; power management products; timing and synchronization devices and precise time solutions, setting the world's standard for time; voice processing devices; RF solutions; discrete components; enterprise storage and communication solutions; security technologies and scalable anti-tamper products; Ethernet solutions; Power-over-Ethernet ICs and midspans; as well as custom design capabilities and services. Microsemi is headquartered in Aliso Viejo, California, and has approximately 4,800 employees globally. Learn more at www.microsemi.com.