

# Clock Generator Selector Guide

Universal clock generators simplify traditional board designs by synthesizing frequencies from either a reference input clock or a common low-cost crystal, providing low-jitter output clocks. When used together with Microsemi clock distribution fanout buffers, the clock generators provide customers with improved board performance and complete timing solutions.

## Any-Rate Clock Synthesis Devices

Product	Independent Output Freq. Families	Inputs	Crystal Input Freq. Range	Xtal Oscillator or CMOS Input Freq. Range	Diff Input Freq. Range	Low-Jitter APLLs	Typical Jitter fs RMS	NCO Mode	NCO ppb	Diff Outputs	CMOS Outputs	Output Freq. Range	NV Memory	Host Bus	Supply Voltage	Pkg Size, mm
MAX24405	2	1 XTAL/SE, 3 D/SE	25 M–52 M	9.72 M–160 M	9.72 M–750 M	2	180 <sup>1</sup>			0–5	0–10	<1 Hz–750 M	Ext EE	SPI	3.3 + 1.8	10 × 10
MAX24505	2	1 XTAL/SE, 3 D/SE	25 M–52 M	9.72 M–160 M	9.72 M–750 M	2	180 <sup>1</sup>			0–5	0–10	<1 Hz–750 M	Int EE	SPI	3.3 + 1.8	10 × 10
MAX24410	2	1 XTAL/SE, 3 D/SE	25 M–52 M	9.72 M–160 M	9.72 M–750 M	2	180 <sup>1</sup>			0–10	0–20	<1 Hz–750 M	Ext EE	SPI	3.3 + 1.8	10 × 10
MAX24510	2	1 XTAL/SE, 3 D/SE	25 M–52 M	9.72 M–160 M	9.72 M–750 M	2	180 <sup>1</sup>			0–10	0–20	<1 Hz–750 M	Int EE	SPI	3.3 + 1.8	10 × 10
ZL30250	1	1 XTAL/SE, 3 D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	1	160 <sup>1</sup>	•	0.01	0–3	0–6	<1 Hz–1035 M <sup>2</sup>	Ext EE <sup>3</sup>	SPI/I2C	3.3 + 1.8	5 × 5
ZL30251	1	1 XTAL/SE, 3 D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	1	160 <sup>1</sup>	•	0.01	0–3	0–6	<1 Hz–1035 M <sup>2</sup>	Int EE <sup>3</sup>	SPI/I2C	3.3 + 1.8	5 × 5
ZL30244	2	2 XTAL/SE, 6 D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	2	160 <sup>1</sup>	•	0.01	0–6	0–12	<1 Hz–1035 M <sup>2</sup>	Ext EE <sup>3</sup>	SPI/I2C	3.3 + 1.8	5 × 10
ZL30245	2	2 XTAL/SE, 6 D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	2	160 <sup>1</sup>	•	0.01	0–6	0–12	<1 Hz–1035 M <sup>2</sup>	Int EE <sup>3</sup>	SPI/I2C	3.3 + 1.8	5 × 10
ZL30260	2	1 XTAL/SE, 3D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	1	170 <sup>1</sup>	•	0.01	0–6	0–12	1 Hz–1035 M <sup>2</sup>	Ext EE <sup>4</sup>	SPI/I2C	Note <sup>5</sup>	8 × 8
ZL30261	2	1 XTAL/SE, 3 D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	1	170 <sup>1</sup>	•	0.01	0–6	0–12	1 Hz–1035 M <sup>2</sup>	Int EE <sup>4</sup>	SPI/I2C	Note <sup>5</sup>	8 × 8
ZL30262	2	1 XTAL/SE, 3 D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	1	170 <sup>1</sup>	•	0.01	0–10	0–20	1 Hz–1035 M <sup>2</sup>	Ext EE <sup>4</sup>	SPI/I2C	Note <sup>5</sup>	8 × 8
ZL30263	2	1 XTAL/SE, 3 D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	1	170 <sup>1</sup>	•	0.01	0–10	0–20	1 Hz–1035 M <sup>2</sup>	Int EE <sup>4</sup>	SPI/I2C	Note <sup>5</sup>	8 × 8
ZL30264	4	1 XTAL/SE, 3 D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	2	170 <sup>1</sup>	•	0.01	0–6	0–12	1 Hz–1035 M <sup>2</sup>	Ext EE <sup>4</sup>	SPI/I2C	Note <sup>5</sup>	8 × 8
ZL30265	4	1 XTAL/SE, 3 D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	2	170 <sup>1</sup>	•	0.01	0–6	0–12	1 Hz–1035 M <sup>2</sup>	Int EE <sup>4</sup>	SPI/I2C	Note <sup>5</sup>	8 × 8
ZL30266	4	1 XTAL/SE, 3 D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	2	170 <sup>1</sup>	•	0.01	0–10	0–20	1 Hz–1035 M <sup>2</sup>	Ext EE <sup>4</sup>	SPI/I2C	Note <sup>5</sup>	8 × 8
ZL30267	4	1 XTAL/SE, 3 D/SE	25 M–60 M	9.72 M–300 M	9.72 M–1250 M	2	170 <sup>1</sup>	•	0.01	0–10	0–20	1 Hz–1035 M <sup>2</sup>	Int EE <sup>4</sup>	SPI/I2C	Note <sup>5</sup>	8 × 8

## Gen 1-4 PCIe Clock Generators

Product	Independent Output Freq. Families	Inputs	Crystal Input Freq. Range	Xtal Oscillator or CMOS Input Freq. Range	Low-Jitter APLLs	Typical Jitter fs RMS	Default Output Configurartions	Output Freq. Range	Host Bus	Supply Voltage	Pkg Size, mm
ZL30281	1	1 XTAL	25M	25 M	1	160	4	25 M, 100 M	SPI/I2C	3.3 + 1.8	5 × 5
ZL30282	2	1 XTAL	50 M	50 M	1	160	8	25 M, 75 M, 100 M	SPI/I2C	Note <sup>5</sup>	8 × 8

Abbreviation Key: D = differential  
 Int EE = internal EEPROM  
 3 = up to four configurations (pin-selectable)

SE = single-ended (CMOS)  
 OTP = one-time programmable  
 4 = up to eight configurations (pin-selectable)

NCO = numerically controlled oscillator  
 1 = integer-mode APLL-only operation  
 5 = 2.5 V only, 3.3 V only, 1.8 V + 2.5 V, 1.8 V + 3.3 V

Ext EE = external EEPROM  
 2 = spread spectrum-capable

# Clock Generator Selector Guide

## Rate Conversion/Jitter Attenuation Devices

Product	Independent Output Freq. Families	Inputs	Crystal Input Freq. Range	Xtal Oscillator or CMOS Input Freq. Range	Diff Input Freq. Range	Low-Jitter APLLs	Typical Jitter fs RMS	DPLL Features: Ref. Switching/ Holdover/ DPLL Bandwidth	NCO Mode	NCO ppb	Diff Outputs	CMOS Outputs	Output Freq. Range	NV Memory	Host Bus	Supply Voltage	Pkg Size, mm
MAX24605	2	1 XTAL/SE, 3 D/SE	25 M–52 M	2 kHz–160 M	2 kHz–750 M	2	180 <sup>1</sup>	Glitchless/ Digital Hold/ 4 Hz–400 Hz	•	<0.001	0–5	0–10	<1 Hz–750 M	Ext EE	SPI	3.3 + 1.8	10 × 10
MAX24610	2	1 XTAL/SE, 3 D/SE	25 M–52 M	2 kHz–160 M	2 kHz–750 M	2	180 <sup>1</sup>	Glitchless/ Digital Hold/ 4 Hz–400 Hz	•	<0.001	0–10	0–20	<1 Hz–750 M	Ext EE	SPI	3.3 + 1.8	10 × 10
ZL30159	1	1 XTAL, 1 D	20 M or 24.578 M	1 Hz–177.5 M	1 Hz–750 M	1	<1000				0	2	1 Hz–177.5 M		SPI/I2C	3.3 + 1.8	9 × 9
ZL30252	1	1 XTAL/SE, 3 D/SE	25 M–60 M	1 kHz–300 M	1 kHz–1250 M	1	160 <sup>1</sup>	Glitchless/ Digital Hold/ 14 Hz–500 Hz	•	0.01	0–3	0–6	<1 Hz–1035 M <sup>2</sup>	Ext EE <sup>3</sup>	SPI/I2C	3.3 + 1.8	5 × 5
ZL30253	1	1 XTAL/SE, 3 D/SE	25 M–60 M	1 kHz–300 M	1 kHz–1250 M	1	160 <sup>1</sup>	Glitchless/ Digital Hold/ 14 Hz–500 Hz	•	0.01	0–3	0–6	<1 Hz–1035 M <sup>2</sup>	Int EE <sup>3</sup>	SPI/I2C	3.3 + 1.8	5 × 5
ZL30254	1	1 XTAL, 2 SE	49.152 MHz	8 kHz or 25 MHz		1	<1 ps	Glitchless/ Digital Hold/ 25 Hz			2	0	125 MHz or 156.25 MHz		None	3.3 + 1.8	5 × 5
ZL30255	2	2 XTAL/SE, 6 D/SE	25 M–60 M	1 kHz–300 M	1 kHz–1250 M	2	160 <sup>1</sup>	Glitchless/ Digital Hold/ 14 Hz–500 Hz	•	0.01	0–6	0–12	<1 Hz–1035 M <sup>2</sup>	Int EE <sup>3</sup>	SPI/I2C	3.3 + 1.8	5 × 10

Abbreviation Key: D = differential  
 Ext EE = external EEPROM  
 1 = integer-mode APLL-only operation

SE = single-ended (CMOS)  
 Int EE = internal EEPROM  
 2 = spread spectrum-capable

NCO = numerically controlled oscillator  
 OTP = one-time programmable  
 3 = up to four configurations pin-selectable



**Microsemi Corporate Headquarters**  
 One Enterprise, Aliso Viejo, CA 92656 USA  
 Within the USA: +1 (800) 713-4113  
 Outside the USA: +1 (949) 380-6100  
 Fax: +1 (949) 215-4996  
 Email: sales.support@microsemi.com  
 www.microsemi.com

Microsemi Corporation (Nasdaq: MSCC) offers a comprehensive portfolio of semiconductor and system solutions for aerospace & defense, communications, data center and industrial markets. Products include high-performance and radiation-hardened analog mixed-signal integrated circuits, FPGAs, SoCs and ASICs; power management products; timing and synchronization devices and precise time solutions, setting the world's standard for time; voice processing devices; RF solutions; discrete components; enterprise storage and communication solutions, security technologies and scalable anti-tamper products; Ethernet solutions; Power-over-Ethernet ICs and midspans; as well as custom design capabilities and services. Microsemi is headquartered in Aliso Viejo, California and has approximately 4,800 employees globally. Learn more at [www.microsemi.com](http://www.microsemi.com).

Microsemi makes no warranty, representation, or guarantee regarding the information contained herein or the suitability of its products and services for any particular purpose, nor does Microsemi assume any liability whatsoever arising out of the application or use of any product or circuit. The products sold hereunder and any other products sold by Microsemi have been subject to limited testing and should not be used in conjunction with mission-critical equipment or applications. Any performance specifications are believed to be reliable but are not verified, and Buyer must conduct and complete all performance and other testing of the products, alone and together with, or installed in, any end-products. Buyer shall not rely on any data and performance specifications or parameters provided by Microsemi. It is the Buyer's responsibility to independently determine suitability of any products and to test and verify the same. The information provided by Microsemi hereunder is provided "as is, where is" and with all faults, and the entire risk associated with such information is entirely with the Buyer. Microsemi does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other IP rights, whether with regard to such information itself or anything described by such information. Information provided in this document is proprietary to Microsemi, and Microsemi reserves the right to make any changes to the information in this document or to any products and services at any time without notice.

©2016 Microsemi Corporation. All rights reserved. Microsemi and the Microsemi logo are registered trademarks of Microsemi Corporation. All other trademarks and service marks are the property of their respective owners.