



a  **MICROCHIP** company

Total Ionizing Dose Test Report

No. 20T-RTAX2000S-CQ352-DGWCJ1

February 2021

Table of Contents

I.	Summary Table	3
II.	Total Ionizing Dose (TID) Testing	3
A.	Device-Under-Test (DUT) and Irradiation Parameters	3
B.	Test Method	4
C.	Design and Parametric Measurements	5
III.	Test Results	6
A.	Functionality.....	6
B.	Power Supply Current (ICCA and ICCI)	6
C.	Single-Ended Input Logic Threshold (VIL/VIH)	10
D.	Differential Input (LVPECL) Threshold Voltage (VIL/VIH)	11
E.	Output-Drive Voltage (VOL/VOH).....	12
F.	Propagation Delay.....	13
G.	Transition Characteristics	15
	Appendix A: DUT Bias	25
	Appendix B: DUT Design Schematics and Verilog Files	27

TOTAL IONIZING DOSE TEST REPORT

No. 20T-RTAX2000S-CQ352-DGWCJ1

December 18, 2020

I. Summary Table

Parameter	Tolerance
1. Gross Functionality	Passed 300 krad (SiO ₂)
2. Power Supply Current (ICCA/ICCI)	Passed 300 krad (SiO ₂)
3. Input Threshold (VTIL/VIH)	Passed 300 krad (SiO ₂)
4. Output Drive (VOL/VOH)	Passed 300 krad (SiO ₂)
5. Propagation Delay	Passed 300 krad (SiO ₂) for 10% degradation criterion
6. Transition Characteristics	Passed 300 krad (SiO ₂)

II. Total Ionizing Dose (TID) Testing

This testing is designed on the base of an extensive database (see TID data of antifuse-based FPGAs at <http://www.klabs.org> and <http://www.microsemi.com/soc>) accumulated from the TID testing of many generations of antifuse-based FPGAs.

A. Device-Under-Test (DUT) and Irradiation Parameters

Table 1 lists the DUT and irradiation parameters. During irradiation, each input and most of the output is grounded through a 1 MΩ resistor; during annealing, each input or output is tied to the ground or VCCI with a 2.7 kΩ resistor. Appendix A contains the schematics of the irradiation-bias circuit.

Table 1 DUT and Irradiation Parameters

Part Number	RTAX2000S
Package	CQ352
Foundry	United Microelectronics Corp.
Technology	0.15 μm CMOS
DUT Design	TOP_AX2000S_TID
Die Lot Number	DGWCJ1
Quantity Tested	5
Serial Number	300 krad(SiO ₂): 7405, 7419 200 krad(SiO ₂): 7373, 7402 100 krad(SiO ₂): 7372
Radiation Facility	Defense Microelectronics Activity
Radiation Source	Co-60
Dose Rate (±5%)	10 krad(SiO ₂)/min
Irradiation Temperature	Room
Irradiation and Measurement Bias (VCCI/VCCA)	Static at 3.3 V/1.5 V

B. Test Method




Figure 1 Parametric Test Flow Chart

The test method generally follows the guidelines in the military standard TM1019.8. Figure 1 is the flow chart describing the steps for functional and parametric tests, irradiation, and post-irradiation annealing.

The accelerated aging, or rebound test mentioned in TM1019.8, is unnecessary; because there is no adverse time-dependent effect (TDE) in Microsemi products manufactured by deep sub-micron CMOS technologies. Elevated temperature annealing basically reduces the effects originating from radiation-induced leakage currents. As indicated by test data in the following sections, the predominant radiation effects in RTAX2000S are due to radiation-induced leakage currents.

Room temperature annealing is performed in this test; the duration is approximately 7 days.

C. Design and Parametric Measurements

The DUT uses a high utilization, generic design (TOP_AX2000S_TID) to evaluate total dose effects for typical space applications. Appendix B contains the schematics and Verilog files of this design.

Table 2 lists measured electrical parameters and the corresponding logic design. The functionality is measured on the output pin (O_BS) of a combinational buffer-string with 14,000 buffers, output pins (O_ANDP_CLKF, O_ORP_CLKF, O_FF_CLKF, O_ANDC_CLKF, O_ORC_CLKF, O_ANDP_CLKG, O_ORP_CLKG, O_FF_CLKG, O_ANDC_CLKG, O_ORC_CLKG, O_ANDP_CLKH, O_ORP_CLKH, O_FF_CLKH, O_ANDC_CLKH, O_ORC_CLKH, O_ANDP_HCLKA, O_ORP_HCLKA, O_FF_HCLKA, O_ANDC_HCLKA, and O_ORC_HCLKA) of four (4) shift registers with 10,728 bits total, and half of the output pins (OUTX0, OUTX1, OUTX2, OUTX3, OUTX4, OUTX5, OUTX6 and OUTX7) of the embedded RAM configured as 16Kx16.

ICC is measured on the power supply of the logic-array (ICCA) and I/O (ICCI) respectively. The input logic threshold (VIL/VIH) is measured on single-ended inputs EN8, DA, IO_I1, IO_I2, IO_I3, IO_I4, IO_I5 and IO_I6, and also on differential inputs DIO_I1P, DIO_I2P, DIO_I3P, DIO_I4P, DIO_I5P, DIO_I6P and DIO_I7P. The differential inputs are configured as LVPECL instead of LVDS; because LVPECL using 3.3 VDC, is worse than LVDS which uses 2.5 VDC. During the measurement on the differential inputs, the N (negative) side of the differential pair is biased at 1.8 V. The output-drive voltage (VOL/VOH) is measured on QA0 and YQ0. The propagation delay is measured on the output (O_BS) of the buffer string; the definition is the time delay from the triggering edge at the CLOCK input to the switching edge at the output O_BS. Both the delays of low-to-high and high-to-low output transitions are measured; the reported delay is the average of these two measurements. The transition characteristics, measured on the output O_BS, are shown as oscilloscope captures.

Table 2 Logic Design for Parametric Measurements

Parameters	Logic Design
1. Functionality	All key logic functions (O_BS, O_ANDP_CLKF, O_ORP_CLKF, O_FF_CLKF, O_ANDC_CLKF, O_ORC_CLKF, O_ANDP_CLKG, O_ORP_CLKG, O_FF_CLKG, O_ANDC_CLKG, O_ORC_CLKG, O_ANDP_CLKH, O_ORP_CLKH, O_FF_CLKH, O_ANDC_CLKH, O_ORC_CLKH, O_ANDP_HCLKA, O_ORP_HCLKA, O_FF_HCLKA, O_ANDC_HCLKA, and O_ORC_HCLKA), and outputs of embedded RAM (OUTX0, OUTX1, OUTX2, OUTX3, OUTX4, OUTX5, OUTX6 and OUTX7)
2. ICC (ICCA/ICCI)	DUT power supply
3. Input Threshold (VIL/VIH)	Single ended inputs (EN8/YQ0, DA/QA0, IO_I1/IO_O1, IO_I2/IO_O2, IO_I3/IO_O3, IO_I4/IO_O4, IO_I5/IO_O5, IO_I6/IO_O6), and differential inputs (DIO_I1P/DIO_O1, DIO_I2P/DIO_O2, DIO_I3P/DIO_O3, DIO_I4P/DIO_O4, DIO_I5P/DIO_O5, DIO_I6P/DIO_O6, DIO_I7P/DIO_O7)
4. Output Drive (VOL/VOH)	Output buffer (EN8/YQ0, DA/QA0)
5. Propagation Delay	String of buffers (CLOCK to O_BS)
6. Transition Characteristic	String of buffers output (O_BS)

III. Test Results

A. Functionality

Every DUT passed the pre-irradiation and post-annealing functional tests. The as-irradiated DUT is functionally tested on the output (O_FF_HCLKA) of the largest shift register.

B. Power Supply Current (ICCA and ICCI)

Figure 2 through Figure 7 plot the influx standby ICCA and ICCI versus total dose for each DUT. The post-annealing ICC for four different bit patterns, all '0', all '1', checkerboard and inverted-checkerboard, in the RAM are basically the same.

Table 3 summarizes the pre-irradiation, post-irradiation right after irradiation and before anneal, and post-annealing ICCA and ICCI data.

Table 3 Pre-Irradiation, Post Irradiation and Post-Annealing ICC

DUT	Total Dose	ICCA (mA)			ICCI (mA)		
		Pre-irrad	Post-irrad	Post-ann	Pre-irrad	Post-irrad	Post-ann
7372	100 krad	12.3	13.5	11.4	28.8	29.9	27.6
7373	200 krad	6.2	7.2	4.9	28.6	58.9	39.9
7402	200 krad	9.0	8.3	9.5	29.2	53.1	37.4
7405	300 krad	12.1	73.3	16.7	66.9	152	92.8
7419	300 krad	5.2	83.3	12.9	28.0	130	59.7




Figure 2 DUT 7405 Influx ICCA and ICCI




Figure 3 DUT 7419 Influx ICCA and ICCI




Figure 4 DUT 7373 Influx ICCA and ICCI




Figure 5 DUT 7402 Influx ICCA and ICCI




Figure 6 DUT 7372 Influx ICCA and ICCI

C. Single-Ended Input Logic Threshold (VIL/VIH)

Table 4a through Table 4c list the pre-irradiation and post-annealing single-ended input logic thresholds. All data are within the specification limits. The post-annealing shift in every case is very small.

Table 4a Pre-Irradiation and Post-Annealing Input Thresholds

DUT	7405 (300 krad)				7419 (300 krad)				
	Input Pin	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann
		VIL (mV)		VIH (mV)		VIL (mV)		VIH (mV)	
DA	1415	1410	1390	1380	1415	1410	1390	1385	
EN8	1395	1390	1390	1380	1380	1395	1395	1385	
IO_I_6	1400	1395	1390	1380	1395	1405	1395	1385	
IO_I_5	1395	1395	1395	1390	1380	1395	1400	1395	
IO_I_4	1385	1380	1385	1385	1390	1385	1390	1385	
IO_I_3	1350	1340	1415	1400	1345	1345	1425	1415	
IO_I_2	1380	1365	1400	1400	1390	1385	1410	1405	
IO_I_1	1380	1365	1395	1390	1385	1385	1405	1400	

Table 4b Pre-Irradiation and Post-Annealing Input Thresholds

DUT	7373 (200 krad)				7402 (200 krad)				
	Input Pin	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann
		VIL (mV)		VIH (mV)		VIL (mV)		VIH (mV)	
DA	1410	1410	1385	1385	1410	1410	1385	1380	
EN8	1390	1352	1385	1380	1385	1395	1390	1385	
IO_I_6	1400	1395	1385	1385	1400	1395	1380	1385	
IO_I_5	1385	1385	1395	1390	1395	1390	1400	1395	
IO_I_4	1400	1380	1385	1380	1385	1400	1390	1390	
IO_I_3	1340	1345	1420	1410	1340	1355	1420	1420	
IO_I_2	1385	1380	1405	1400	1380	1375	1405	1400	
IO_I_1	1380	1375	1400	1395	1385	1385	1395	1400	

Table 4c Pre-Irradiation and Post-Annealing Input Thresholds

DUT	7372 (100 krad)				
	Input Pin	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann
		VIL (mV)		VIH (mV)	
DA	1405	1395	1390	1385	
EN8	1435	1390	1385	1385	
IO_I_6	1395	1390	1390	1385	
IO_I_5	1390	1390	1400	1390	
IO_I_4	1385	1395	1390	1385	
IO_I_3	1360	1350	1420	1415	
IO_I_2	1385	1380	1405	1400	
IO_I_1	1385	1375	1400	1400	

D. Differential Input (LVPECL) Threshold Voltage (VIL/VIH)

Table 5a through Table 5c list the LVPECL differential input threshold voltage changes due to irradiations. All pins show negligible changes, and all the data are within the specification.

Table 5a Pre-Irradiation and Post-Annealing Differential Input Thresholds

DUT	7405 (300 krad)				7419 (300 krad)				
	Input Pin	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann
VIL (mV)		VIH (mV)		VIL (mV)		VIH (mV)			
DIO_IP_1	DIO_IP_1	1790	1790	1785	1785	1790	1785	1785	1785
DIO_IP_2	DIO_IP_2	1785	1785	1785	1785	1780	1785	1785	1790
DIO_IP_3	DIO_IP_3	1790	1795	1785	1790	1790	1790	1785	1785
DIO_IP_4	DIO_IP_4	1780	1790	1790	1790	1780	1780	1790	1790
DIO_IP_5	DIO_IP_5	1790	1790	1785	1785	1790	1790	1785	1785
DIO_IP_6	DIO_IP_6	1780	1780	1790	1790	1780	1780	1785	1785
DIO_IP_7	DIO_IP_7	1795	1795	1790	1790	1790	1790	1785	1790

Table 5b Pre-Irradiation and Post-Annealing Differential Input Thresholds

DUT	7373 (200 krad)				7402 (200 krad)				
	Input Pin	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann
VIL (mV)		VIH (mV)		VIL (mV)		VIH (mV)			
DIO_IP_1	DIO_IP_1	1795	1795	1790	1790	1795	1795	1790	1790
DIO_IP_2	DIO_IP_2	1785	1790	1790	1790	1790	1795	1795	1795
DIO_IP_3	DIO_IP_3	1795	1795	1790	1790	1795	1795	1790	1790
DIO_IP_4	DIO_IP_4	1785	1790	1790	1790	1785	1785	1795	1795
DIO_IP_5	DIO_IP_5	1790	1790	1790	1790	1795	1795	1790	1790
DIO_IP_6	DIO_IP_6	1780	1780	1785	1785	1780	1780	1790	1790
DIO_IP_7	DIO_IP_7	1790	1790	1785	1790	1790	1790	1790	1790

Table 5c Pre-Irradiation and Post-Annealing Differential Input Thresholds

DUT	7372 (100 krad)				
	Input Pin	Pre-Irrad	Post-Ann	Pre-Irrad	Post-Ann
VIL (mV)		VIH (mV)			
DIO_IP_1	DIO_IP_1	1795	1795	1790	1790
DIO_IP_2	DIO_IP_2	1790	1790	1795	1795
DIO_IP_3	DIO_IP_3	1795	1795	1790	1790
DIO_IP_4	DIO_IP_4	1780	1785	1790	1790
DIO_IP_5	DIO_IP_5	1795	1795	1790	1790
DIO_IP_6	DIO_IP_6	1790	1780	1790	1790
DIO_IP_7	DIO_IP_7	1790	1790	1790	1790

E. Output-Drive Voltage (VOL/VOH)

The pre-irradiation and post-annealing VOL/VOH are listed in Tables 6 and 7. The post-annealing data are within the specification limits.

Table 6 Pre-Irradiation and Post-Annealing VOL (mV) at Various Sinking Current

Sourcing Current	Pin\DUT	7405 (300 krad)		7419 (300 krad)		7373 (200 krad)		7402 (200 krad)		7372 (100 krad)	
		Pre-rad	Post-an								
1 mA	QA0	7	8	8	8	8	8	7	8	7	8
	YQ0	9	8	9	8	9	9	8	9	8	8
12 mA	QA0	91	89	89	88	91	92	89	90	89	90
	YQ0	103	99	102	97	101	102	100	101	100	99
20 mA	QA0	152	148	150	147	152	153	149	150	149	151
	YQ0	171	164	170	162	169	171	167	169	168	165
50 mA	QA0	388	378	382	373	387	388	378	381	381	383
	YQ0	436	416	432	412	430	432	423	427	427	418
100 mA	QA0	824	798	811	790	821	819	804	806	808	811
	YQ0	919	875	912	868	907	907	893	898	899	881

Table 7 Pre-Irradiation and Post-Annealing VOH (mV) at Various Sourcing Current

Sourcing Current	Pin\DUT	7405 (300 krad)		7419 (300 krad)		7373 (200 krad)		7402 (200 krad)		7372 (100 krad)	
		Pre-rad	Post-an								
1 mA	QA0	3287	3288	3288	3288	3287	3288	3288	3288	3288	3290
	YQ0	3286	3284	3286	3284	3286	3287	3286	3288	3286	3287
8 mA	QA0	3222	3221	3222	3222	3221	3220	3222	3221	3223	3224
	YQ0	3215	3213	3215	3213	3214	3214	3215	3214	3216	3216
20 mA	QA0	3109	3106	3109	3106	3106	3102	3108	3104	3110	3108
	YQ0	3091	3089	3091	3088	3090	3085	3091	3086	3094	3093
50 mA	QA0	2810	2802	2812	2803	2805	2791	2810	2796	2816	2806
	YQ0	2770	2768	2770	2767	2767	2751	2771	2756	2776	2773
100 mA	QA0	2233	2214	2238	2217	2221	2192	2231	2201	2248	2223
	YQ0	2157	2151	2158	2150	2147	2113	2157	2124	2170	2162

F. Propagation Delay

The propagation delay was measured in-situ, post-irradiation, and post-annealing. The results are plotted in Figure 7, and listed in Table 8. As shown in Figure 8, the propagation delay moves with the total dose, but the change is small throughout the irradiation. Referring to influx static current plots (Figure 2 through Figure 6), a device probably heats up as the dose increases. The rising temperature could be the root cause of the increasing trend at high doses. The post-annealing data, on the other hand, show decreased delay in every case.

The radiation delta in every case is well within the 10% degradation criterion. The user can take the worst case for the design margin consideration.




Figure 7 In-Situ Propagation Delay versus Total Dose

Table 8 Radiation-Induced Propagation Delay Degradations

Delay (μs)	DUT	Total Dose	Pre-rad	100 krad	200 krad	300 krad	Post-ann
Radiation Δ (%)	7405	300 krad	6.20	6.20	6.22	6.47	6.10
	7419	300 krad	6.45	6.41	6.44	6.77	6.33
	7373	200 krad	6.55	6.54	6.56	-	6.45
	7402	200 krad	6.74	6.73	6.74	-	6.63
	7372	100 krad	6.12	6.11	-	-	6.04
	DUT	Total Dose	Pre-rad	100 krad	200 krad	300 krad	Post-ann
Radiation Δ (%)	7405	300 krad	-	0.08%	0.40%	4.44%	-1.53%
	7419	300 krad	-	-0.54%	-0.08%	4.97%	-1.78%
	7373	200 krad	-	-0.15%	0.15%	-	-1.53%
	7402	200 krad	-	-0.15%	-0.07%	-	-1.63%
	7372	100 krad	-	-0.16%	-	-	-1.31%

G. Transition Characteristics


Figure 8a to Figure 17b show the pre-irradiation and post-annealing transition edges. In each case, the radiation-induced transition-time degradation is insignificant.



Figure 8a DUT 7405 Pre-Irradiation Rising Edge



Figure 8b DUT 7405 Post-Annealing Rising Edge


Figure 9a DUT 7419 Pre-Irradiation Rising Edge

Figure 9b DUT 7419 Post-Annealing Rising Edge






Figure 10a DUT 7373 Pre-Radiation Rising Edge

Figure 10b DUT 7373 Post-Annealing Rising edge


Figure 11a DUT 7402 Pre-Irradiation Rising Edge

Figure 11b DUT 7402 Post-Annealing Rising Edge


Figure 12a DUT 7372 Pre-Irradiation Rising Edge

Figure 12b DUT 7372 Post-Annealing Rising Edge




Figure 13a DUT 7405 Pre-Radiation Falling Edge

Figure 13b DUT 7405 Post-Annealing Falling Edge



Figure 14a DUT 7419 Pre-Irradiation Falling Edge










Figure 14b DUT 7419 Post-Annealing Falling Edge


Figure 15a DUT 7373 Pre-Irradiation Falling Edge

Figure 15b DUT 7373 Post-Annealing Falling Edge


Figure 16a DUT 7402 Pre-Irradiation Falling Edge

Figure 16b DUT 7402 Post-Annealing Falling Edge


Figure 17a DUT 7372 Pre-Irradiation Falling Edge

Figure 17b DUT 7372 Post-Annealing Falling Edge

Appendix A: DUT Bias




Figure A1 I/O Bias During Irradiation









Figure A2 Power Supply, Ground and Special Pins Bias During Irradiation


Appendix B: DUT Design Schematics and Verilog Files




















```

// BUFF2p3k.v
`timescale 1 ns/100ps

module BUFF2p3k (In, Out);

input In;
output Out;

wire x1/*synthesis syn_keep=1 alspreserve=1*/;
wire x2/*synthesis syn_keep=1 alspreserve=1*/;
wire x3/*synthesis syn_keep=1 alspreserve=1*/;
wire x4/*synthesis syn_keep=1 alspreserve=1*/;
wire x5/*synthesis syn_keep=1 alspreserve=1*/;
wire x6/*synthesis syn_keep=1 alspreserve=1*/;
wire x7/*synthesis syn_keep=1 alspreserve=1*/;

BUFF1k buff1k_1 (.In(In), .Out(x1));
BUFF1k buff1k_2 (.In(x1), .Out(x2));
BUFF50 buff3 (.In(x2), .Out(x3));
BUFF50 buff4 (.In(x3), .Out(x4));
BUFF50 buff5 (.In(x4), .Out(x5));
BUFF50 buff6 (.In(x5), .Out(x6));
BUFF50 buff7 (.In(x6), .Out(x7));
BUFF50 buff8 (.In(x7), .Out(Out));

endmodule

// BUFF1k
`timescale 1 ns/100ps

module BUFF1k (In, Out);

input In;
output Out;

wire x1/*synthesis syn_keep=1 alspreserve=1*/;
wire x2/*synthesis syn_keep=1 alspreserve=1*/;
wire x3/*synthesis syn_keep=1 alspreserve=1*/;
wire x4/*synthesis syn_keep=1 alspreserve=1*/;
wire x5/*synthesis syn_keep=1 alspreserve=1*/;
wire x6/*synthesis syn_keep=1 alspreserve=1*/;
wire x7/*synthesis syn_keep=1 alspreserve=1*/;
wire x8/*synthesis syn_keep=1 alspreserve=1*/;
wire x9/*synthesis syn_keep=1 alspreserve=1*/;
wire x10/*synthesis syn_keep=1 alspreserve=1*/;
wire x11/*synthesis syn_keep=1 alspreserve=1*/;
wire x12/*synthesis syn_keep=1 alspreserve=1*/;
wire x13/*synthesis syn_keep=1 alspreserve=1*/;
wire x14/*synthesis syn_keep=1 alspreserve=1*/;
wire x15/*synthesis syn_keep=1 alspreserve=1*/;
wire x16/*synthesis syn_keep=1 alspreserve=1*/;
wire x17/*synthesis syn_keep=1 alspreserve=1*/;
wire x18/*synthesis syn_keep=1 alspreserve=1*/;
wire x19/*synthesis syn_keep=1 alspreserve=1*/;

```

```

BUFF50 buff1(.In(In), .Out(x1));
BUFF50 buff2(.In(x1), .Out(x2));
BUFF50 buff3(.In(x2), .Out(x3));
BUFF50 buff4(.In(x3), .Out(x4));
BUFF50 buff5(.In(x4), .Out(x5));
BUFF50 buff6(.In(x5), .Out(x6));
BUFF50 buff7(.In(x6), .Out(x7));
BUFF50 buff8(.In(x7), .Out(x8));
BUFF50 buff9(.In(x8), .Out(x9));
BUFF50 buff10(.In(x9), .Out(x10));

BUFF50 buff11(.In(x10), .Out(x11));
BUFF50 buff12(.In(x11), .Out(x12));
BUFF50 buff13(.In(x12), .Out(x13));
BUFF50 buff14(.In(x13), .Out(x14));
BUFF50 buff15(.In(x14), .Out(x15));
BUFF50 buff16(.In(x15), .Out(x16));
BUFF50 buff17(.In(x16), .Out(x17));
BUFF50 buff18(.In(x17), .Out(x18));
BUFF50 buff19(.In(x18), .Out(x19));
BUFF50 buff20(.In(x19), .Out(Out));

endmodule

// BUFF50
`timescale 1 ns/100 ps

module BUFF50 (In, Out);

input In;
output Out;

wire x1 /*synthesis syn_keep=1 alspreserve=1*/;
wire x2 /*synthesis syn_keep=1 alspreserve=1*/;
wire x3 /*synthesis syn_keep=1 alspreserve=1*/;
wire x4 /*synthesis syn_keep=1 alspreserve=1*/;
wire x5 /*synthesis syn_keep=1 alspreserve=1*/;
wire x6 /*synthesis syn_keep=1 alspreserve=1*/;
wire x7 /*synthesis syn_keep=1 alspreserve=1*/;
wire x8 /*synthesis syn_keep=1 alspreserve=1*/;
wire x9 /*synthesis syn_keep=1 alspreserve=1*/;
wire x10 /*synthesis syn_keep=1 alspreserve=1*/;
wire x11 /*synthesis syn_keep=1 alspreserve=1*/;
wire x12 /*synthesis syn_keep=1 alspreserve=1*/;
wire x13 /*synthesis syn_keep=1 alspreserve=1*/;
wire x14 /*synthesis syn_keep=1 alspreserve=1*/;
wire x15 /*synthesis syn_keep=1 alspreserve=1*/;
wire x16 /*synthesis syn_keep=1 alspreserve=1*/;
wire x17 /*synthesis syn_keep=1 alspreserve=1*/;
wire x18 /*synthesis syn_keep=1 alspreserve=1*/;
wire x19 /*synthesis syn_keep=1 alspreserve=1*/;
wire x20 /*synthesis syn_keep=1 alspreserve=1*/;
wire x21 /*synthesis syn_keep=1 alspreserve=1*/;
wire x22 /*synthesis syn_keep=1 alspreserve=1*/;
```

```

wire x23/*synthesis syn_keep=1 alspreserve=1*/;
wire x24/*synthesis syn_keep=1 alspreserve=1*/;
wire x25/*synthesis syn_keep=1 alspreserve=1*/;
wire x26/*synthesis syn_keep=1 alspreserve=1*/;
wire x27/*synthesis syn_keep=1 alspreserve=1*/;
wire x28/*synthesis syn_keep=1 alspreserve=1*/;
wire x29/*synthesis syn_keep=1 alspreserve=1*/;
wire x30/*synthesis syn_keep=1 alspreserve=1*/;
wire x31/*synthesis syn_keep=1 alspreserve=1*/;
wire x32/*synthesis syn_keep=1 alspreserve=1*/;
wire x33/*synthesis syn_keep=1 alspreserve=1*/;
wire x34/*synthesis syn_keep=1 alspreserve=1*/;
wire x35/*synthesis syn_keep=1 alspreserve=1*/;
wire x36/*synthesis syn_keep=1 alspreserve=1*/;
wire x37/*synthesis syn_keep=1 alspreserve=1*/;
wire x38/*synthesis syn_keep=1 alspreserve=1*/;
wire x39/*synthesis syn_keep=1 alspreserve=1*/;
wire x40/*synthesis syn_keep=1 alspreserve=1*/;
wire x41/*synthesis syn_keep=1 alspreserve=1*/;
wire x42/*synthesis syn_keep=1 alspreserve=1*/;
wire x43/*synthesis syn_keep=1 alspreserve=1*/;
wire x44/*synthesis syn_keep=1 alspreserve=1*/;
wire x45/*synthesis syn_keep=1 alspreserve=1*/;
wire x46/*synthesis syn_keep=1 alspreserve=1*/;
wire x47/*synthesis syn_keep=1 alspreserve=1*/;
wire x48/*synthesis syn_keep=1 alspreserve=1*/;
wire x49/*synthesis syn_keep=1 alspreserve=1*/;
```

```

BUFFbuff1(.A(In), .Y(x1));
BUFFbuff2(.A(x1), .Y(x2));
BUFFbuff3(.A(x2), .Y(x3));
BUFFbuff4(.A(x3), .Y(x4));
BUFFbuff5(.A(x4), .Y(x5));
BUFFbuff6(.A(x5), .Y(x6));
BUFFbuff7(.A(x6), .Y(x7));
BUFFbuff8(.A(x7), .Y(x8));
BUFFbuff9(.A(x8), .Y(x9));
BUFFbuff10(.A(x9), .Y(x10));
```

```

BUFFbuff11(.A(x10), .Y(x11));
BUFFbuff12(.A(x11), .Y(x12));
BUFFbuff13(.A(x12), .Y(x13));
BUFFbuff14(.A(x13), .Y(x14));
BUFFbuff15(.A(x14), .Y(x15));
BUFFbuff16(.A(x15), .Y(x16));
BUFFbuff17(.A(x16), .Y(x17));
BUFFbuff18(.A(x17), .Y(x18));
BUFFbuff19(.A(x18), .Y(x19));
BUFFbuff20(.A(x19), .Y(x20));
```

```

BUFFbuff21(.A(x20), .Y(x21));
BUFFbuff22(.A(x21), .Y(x22));
BUFFbuff23(.A(x22), .Y(x23));
BUFFbuff24(.A(x23), .Y(x24));
BUFFbuff25(.A(x24), .Y(x25));
BUFFbuff26(.A(x25), .Y(x26));
```

```

BUFFbuff27(.A(x26), .Y(x27));
BUFFbuff28(.A(x27), .Y(x28));
BUFFbuff29(.A(x28), .Y(x29));
BUFFbuff30(.A(x29), .Y(x30));

BUFFbuff31(.A(x30), .Y(x31));
BUFFbuff32(.A(x31), .Y(x32));
BUFFbuff33(.A(x32), .Y(x33));
BUFFbuff34(.A(x33), .Y(x34));
BUFFbuff35(.A(x34), .Y(x35));
BUFFbuff36(.A(x35), .Y(x36));
BUFFbuff37(.A(x36), .Y(x37));
BUFFbuff38(.A(x37), .Y(x38));
BUFFbuff39(.A(x38), .Y(x39));
BUFFbuff40(.A(x39), .Y(x40));

BUFFbuff41(.A(x40), .Y(x41));
BUFFbuff42(.A(x41), .Y(x42));
BUFFbuff43(.A(x42), .Y(x43));
BUFFbuff44(.A(x43), .Y(x44));
BUFFbuff45(.A(x44), .Y(x45));
BUFFbuff46(.A(x45), .Y(x46));
BUFFbuff47(.A(x46), .Y(x47));
BUFFbuff48(.A(x47), .Y(x48));
BUFFbuff49(.A(x48), .Y(x49));
BUFFbuff50(.A(x49), .Y(Out));

endmodule

// FF128
`timescale 1 ns/100ps
module FF128 (D, Q, CLK, RST, ANDP, ORP, ANDC, ORC);

input D, CLK, RST;
output Q, ANDP, ORP, ANDC, ORC;

wire x1, x2, x3, Q;
wire andp_a, andp_b, andp_c, andp_d, orp_a, orp_b, orp_c, orp_d;
wire andc_a, andc_b, andc_c, andc_d, orc_a, orc_b, orc_c, orc_d;

FF32 dff_a(.D(D), .Q(x1), .CLK(CLK), .RST(RST), .ANDP(andp_a), .ORP(orp_a),
.ANDC(andc_a), .ORC(orc_a));

FF32 dff_b(.D(x1), .Q(x2), .CLK(CLK), .RST(RST), .ANDP(andp_b), .ORP(orp_b),
.ANDC(andc_b), .ORC(orc_b));

FF32 dff_c(.D(x2), .Q(x3), .CLK(CLK), .RST(RST), .ANDP(andp_c), .ORP(orp_c),
.ANDC(andc_c), .ORC(orc_c));

FF32 dff_d(.D(x3), .Q(Q), .CLK(CLK), .RST(RST), .ANDP(andp_d), .ORP(orp_d),
.ANDC(andc_d), .ORC(orc_d));

AND4 and4p (.A(andp_a), .B(andp_b), .C(andp_c), .D(andp_d), .Y(ANDP));
OR4 or4p (.A(orp_a), .B(orp_b), .C(orp_c), .D(orp_d), .Y(ORP));

AND4 and4c (.A(andc_a), .B(andc_b), .C(andc_c), .D(andc_d), .Y(ANDC));

```

```

OR4 or4c (.A(orc_a), .B(orc_b), .C(orc_c), .D(orc_d), .Y(ORC));

endmodule

// FF32
`timescale 1 ns/100ps
module FF32(D, Q, CLK, RST, ANDP, ORP, ANDC, ORC);

input D, CLK, RST;
output Q, ANDP, ORP, ANDC, ORC;

wire x1, x2, x3, Q;
wire andp_a, andp_b, andp_c, andp_d, orp_a, orp_b, orp_c, orp_d;
wire andc_a, andc_b, andc_c, andc_d, orc_a, orc_b, orc_c, orc_d;

FF8 dff_a(.D(D), .Q(x1), .CLK(CLK), .RST(RST), .ANDP(andp_a), .ORP(orp_a),
.ANDC(andc_a), .ORC(orc_a));

FF8 dff_b(.D(x1), .Q(x2), .CLK(CLK), .RST(RST), .ANDP(andp_b), .ORP(orp_b),
.ANDC(andc_b), .ORC(orc_b));

FF8 dff_c(.D(x2), .Q(x3), .CLK(CLK), .RST(RST), .ANDP(andp_c), .ORP(orp_c),
.ANDC(andc_c), .ORC(orc_c));

FF8 dff_d(.D(x3), .Q(Q), .CLK(CLK), .RST(RST), .ANDP(andp_d), .ORP(orp_d),
.ANDC(andc_d), .ORC(orc_d));

AND4 and4p (.A(andp_a), .B(andp_b), .C(andp_c), .D(andp_d), .Y(ANDP));
OR4 or4p (.A(orp_a), .B(orp_b), .C(orp_c), .D(orp_d), .Y(ORP));

AND4 and4c (.A(andc_a), .B(andc_b), .C(andc_c), .D(andc_d), .Y(ANDC));
OR4 or4c (.A(orc_a), .B(orc_b), .C(orc_c), .D(orc_d), .Y(ORC));

endmodule

// FF8
`timescale 1 ns/100ps

module FF8(D, Q, CLK, RST, ANDP, ORP, ANDC, ORC);

input D, CLK, RST;
output Q, ANDP, ORP, ANDC, ORC;

wire x1, x2, x3, x4, x5, x6, x7;

DFC1B dff1(.D(D), .Q(x1), .CLK(CLK), .CLR(RST));
DFP1B dff2(.D(x1), .Q(x2), .CLK(CLK), .PRE(RST));
DFC1B dff3(.D(x2), .Q(x3), .CLK(CLK), .CLR(RST));
DFP1B dff4(.D(x3), .Q(x4), .CLK(CLK), .PRE(RST));
DFC1B dff5(.D(x4), .Q(x5), .CLK(CLK), .CLR(RST));
DFP1B dff6(.D(x5), .Q(x6), .CLK(CLK), .PRE(RST));
DFC1B dff7(.D(x6), .Q(x7), .CLK(CLK), .CLR(RST));
DFP1B dff8(.D(x7), .Q(Q), .CLK(CLK), .PRE(RST));

AND4 and4p (.A(x2), .B(x4), .C(x6), .D(Q), .Y(ANDP));
OR4 or4p (.A(x2), .B(x4), .C(x6), .D(Q), .Y(ORP));

```

AND4 and4c (.A(x1), .B(x3), .C(x5), .D(x7), .Y(ANDC));
 OR4 or4c (.A(x1), .B(x3), .C(x5), .D(x7), .Y(ORC));

endmodule

```
// Top_RAM_Module.v
`timescale 1 ns/100ps
```

```
module Top_RAM_Module(Psel0, Psel1, RC_en, RC_clr, RC_clk, Write, Read, Wclk, Rclk,
                      Q_RAM);
```

```
input Psel0, Psel1, RC_en, RC_clr, RC_clk, Write, Read, Wclk, Rclk;
output [5:0] Q_RAM;
```

```
wire Gnd, Vcc;
wire mx0, mx1;
wire [12:0] rc;
wire [3:0] dec;
wire y_0w, y_0r, y_1w, y_1r, y_2w, y_2r, y_3w, y_3r;
// y_4w, y_4r, y_5w, y_5r, y_6w, y_6r, y_7w, y_7r;
wire [5:0] DIN;
wire [5:0] Q_b0;
wire [5:0] Q_b1;
wire [5:0] Q_b2;
wire [5:0] Q_b3;
//wire [5:0] Q_b4;
//wire [5:0] Q_b5;
//wire [5:0] Q_b6;
//wire [5:0] Q_b7;
```

```
GND gnd_0(.Y(Gnd));
VCC vcc_0(.Y(Vcc));
```

```
mux_2x1 mux_0(.Data0_port(Gnd), .Data1_port(Vcc), .Sel0(Psel0), .Result(mx0));
mux_2x1 mux_1(.Data0_port(Gnd), .Data1_port(Vcc), .Sel0(Psel1), .Result(mx1));
```

```
counter_13 counter_0(.Enable(RC_en), .Aclr(RC_clr), .Clock(RC_clk), .Q(rc));
```

```
decoder_2to4 decoder_0(.Data0(rc[11]), .Data1(rc[12]), .Eq(dec));
```

```
NAND2 nand_0w(.A(dec[0]), .B(Write), .Y(y_0w));
NAND2 nand_0r(.A(dec[0]), .B(Read), .Y(y_0r));
```

```
ram_2048x6 ram_blk0(.Data(DIN), .Q(Q_b0), .WAddress(rc[10:0]), .RAddress(rc[10:0]),
                     .WE(y_0w), .RE(y_0r), .WClock(Wclk), .RClock(Rclk));
```

```
assign DIN[0]=mx0, DIN[1]=mx1, DIN[2]=mx0, DIN[3]=mx1, DIN[4]=mx0, DIN[5]=mx1;
```

```
NAND2 nand_1w(.A(dec[1]), .B(Write), .Y(y_1w));
NAND2 nand_1r(.A(dec[1]), .B(Read), .Y(y_1r));
```

```
ram_2048x6 ram_blk1(.Data(DIN), .Q(Q_b1), .WAddress(rc[10:0]), .RAddress(rc[10:0]),
                     .WE(y_1w), .RE(y_1r), .WClock(Wclk), .RClock(Rclk));
```

```
NAND2 nand_2w(.A(dec[2]), .B(Write), .Y(y_2w));
NAND2 nand_2r(.A(dec[2]), .B(Read), .Y(y_2r));
```

```

ram_2048x6 ram_blk2(.Data(DIN),
  .Q(Q_b2), .WAddress(rc[10:0]), .RAddress(rc[10:0]),
  .WE(y_2w), .RE(y_2r), .WClock(Wclk), .RClock(Rclk));

NAND2 nand_3w(.A(dec[3]), .B(Write), .Y(y_3w));
NAND2 nand_3r(.A(dec[3]), .B(Read), .Y(y_3r));

ram_2048x6 ram_blk3(.Data(DIN),
  .Q(Q_b3), .WAddress(rc[10:0]), .RAddress(rc[10:0]),
  .WE(y_3w), .RE(y_3r), .WClock(Wclk), .RClock(Rclk));

/* NAND2 nand_4w(.A(dec[4]), .B(Write), .Y(y_4w));
NAND2 nand_4r(.A(dec[4]), .B(Read), .Y(y_4r));

ram_2048x3 ram_blk4(.Data(DIN),
  .Q(Q_b4), .WAddress(rc[10:0]), .RAddress(rc[10:0]),
  .WE(y_4w), .RE(y_4r), .WClock(Wclk), .RClock(Rclk));

NAND2 nand_5w(.A(dec[5]), .B(Write), .Y(y_5w));
NAND2 nand_5r(.A(dec[5]), .B(Read), .Y(y_5r));

ram_2048x3 ram_blk5(.Data(DIN),
  .Q(Q_b5), .WAddress(rc[10:0]), .RAddress(rc[10:0]),
  .WE(y_5w), .RE(y_5r), .WClock(Wclk), .RClock(Rclk));

NAND2 nand_6w(.A(dec[6]), .B(Write), .Y(y_6w));
NAND2 nand_6r(.A(dec[6]), .B(Read), .Y(y_6r));

ram_2048x3 ram_blk6(.Data(DIN),
  .Q(Q_b6), .WAddress(rc[10:0]), .RAddress(rc[10:0]),
  .WE(y_6w), .RE(y_6r), .WClock(Wclk), .RClock(Rclk));

NAND2 nand_7w(.A(dec[7]), .B(Write), .Y(y_7w));
NAND2 nand_7r(.A(dec[7]), .B(Read), .Y(y_7r));

ram_2048x3 ram_blk7(.Data(DIN),
  .Q(Q_b7), .WAddress(rc[10:0]), .RAddress(rc[10:0]),
  .WE(y_7w), .RE(y_7r), .WClock(Wclk), .RClock(Rclk)); */

mux_6x4 mux_6x4_0(.Data0_port(Q_b0), .Data1_port(Q_b1), .Data2_port(Q_b2),
  .Data3_port(Q_b3), .Sel0(rc[11]), .Sel1(rc[12]), .Result(Q_RAM));

```

endmodule

`timescale 1 ns/100ps
 // Version: 6.0 SP3 6.0.30.3

```
module mux_2x1(Data0_port,Data1_port,Sel0,Result);
input Data0_port, Data1_port, Sel0;
output Result;

MX2 MX2_Result(.A(Data0_port), .B(Data1_port), .S(Sel0), .Y(
  Result));

endmodule
```

`timescale 1 ns/100ps
 // Version: 6.2 SP2 6.2.52.7

```
module counter_13(Enable,Aclr,Clock,Q);
input Enable, Aclr, Clock;
output [12:0] Q;

wire ClrAux_0_net,ClrAux_7_net,MX2_1_Y,MX2_7_Y,MX2_4_Y,
  CM8_0_Y,MX2_10_Y,MX2_9_Y,MX2_3_Y,MX2_5_Y,MX2_6_Y,
  MX2_0_Y,MX2_8_Y,MX2_2_Y,MX2_11_Y,VCC,GND;

VCC VCC_1_net(.Y(VCC));
GND GND_1_net(.Y(GND));
DFC1D DFC1D_Q_7_inst(.D(MX2_1_Y), .CLK(Q[6]), .CLR(
  ClrAux_7_net), .Q(Q[7]));
DFC1D DFC1D_Q_1_inst(.D(MX2_7_Y), .CLK(Q[0]), .CLR(
  ClrAux_0_net), .Q(Q[1]));
BUFFBUFF_ClrAux_0_inst(.A(Aclr), .Y(ClrAux_0_net));
MX2 MX2_9_(.A(VCC), .B(GND), .S(Q[5]), .Y(MX2_9_Y));
DFC1D DFC1D_Q_2_inst(.D(MX2_6_Y), .CLK(Q[1]), .CLR(
  ClrAux_0_net), .Q(Q[2]));
MX2 MX2_0_(.A(VCC), .B(GND), .S(Q[8]), .Y(MX2_0_Y));
DFC1D DFC1D_Q_12_inst(.D(MX2_4_Y), .CLK(Q[11]), .CLR(
  ClrAux_7_net), .Q(Q[12]));
DFC1D DFC1D_Q_3_inst(.D(MX2_11_Y), .CLK(Q[2]), .CLR(
  ClrAux_0_net), .Q(Q[3]));
DFC1D DFC1D_Q_4_inst(.D(MX2_5_Y), .CLK(Q[3]), .CLR(
  ClrAux_0_net), .Q(Q[4]));
CM8 CM8_0_(.D0(GND), .D1(VCC), .D2(VCC), .D3(GND), .S00(Q[0]),
  .S01(VCC), .S10(Enable), .S11(GND), .Y(CM8_0_Y));
MX2 MX2_11_(.A(VCC), .B(GND), .S(Q[3]), .Y(MX2_11_Y));
DFC1B DFC1B_Q_0_inst(.D(CM8_0_Y), .CLK(Clock), .CLR(
  ClrAux_0_net), .Q(Q[0]));
MX2 MX2_6_(.A(VCC), .B(GND), .S(Q[2]), .Y(MX2_6_Y));
MX2 MX2_3_(.A(VCC), .B(GND), .S(Q[10]), .Y(MX2_3_Y));
DFC1D DFC1D_Q_11_inst(.D(MX2_10_Y), .CLK(Q[10]), .CLR(
  ClrAux_7_net), .Q(Q[11]));
MX2 MX2_10_(.A(VCC), .B(GND), .S(Q[11]), .Y(MX2_10_Y));
BUFFBUFF_ClrAux_7_inst(.A(Aclr), .Y(ClrAux_7_net));
MX2 MX2_4_(.A(VCC), .B(GND), .S(Q[12]), .Y(MX2_4_Y));
DFC1D DFC1D_Q_5_inst(.D(MX2_9_Y), .CLK(Q[4]), .CLR(
```

```

  ClrAux_0_net), .Q(Q[5]));
  DFC1D DFC1D_Q_9_inst(.D(MX2_8_Y), .CLK(Q[8]), .CLR(
    ClrAux_7_net), .Q(Q[9]));
  MX2 MX2_5.(A(VCC), .B(GND), .S(Q[4]), .Y(MX2_5_Y));
  MX2 MX2_8.(A(VCC), .B(GND), .S(Q[9]), .Y(MX2_8_Y));
  DFC1D DFC1D_Q_8_inst(.D(MX2_0_Y), .CLK(Q[7]), .CLR(
    ClrAux_7_net), .Q(Q[8]));
  MX2 MX2_2.(A(VCC), .B(GND), .S(Q[6]), .Y(MX2_2_Y));
  MX2 MX2_7.(A(VCC), .B(GND), .S(Q[1]), .Y(MX2_7_Y));
  MX2 MX2_1.(A(VCC), .B(GND), .S(Q[7]), .Y(MX2_1_Y));
  DFC1D DFC1D_Q_6_inst(.D(MX2_2_Y), .CLK(Q[5]), .CLR(
    ClrAux_0_net), .Q(Q[6]));
  DFC1D DFC1D_Q_10_inst(.D(MX2_3_Y), .CLK(Q[9]), .CLR(
    ClrAux_7_net), .Q(Q[10]));

endmodule

`timescale 1 ns/100ps
// Version: 6.2 SP2 6.2.52.7

```

```

module decoder_2to4(Data0,Data1,Eq);
input Data0, Data1;
output [3:0] Eq;

AND2A AND2A_Eq_1_inst(.A(Data1), .B(Data0), .Y(Eq[1]));
AND2 AND2_Eq_3_inst(.A(Data0), .B(Data1), .Y(Eq[3]));
AND2A AND2A_Eq_2_inst(.A(Data0), .B(Data1), .Y(Eq[2]));
AND2B AND2B_Eq_0_inst(.A(Data0), .B(Data1), .Y(Eq[0]));

```

```

endmodule

`timescale 1 ns/100ps
// Version: 6.2 SP2 6.2.52.7

```

```

module ram_2048x6(Data,Q,WAddress,RAddress,WE,RE,WClock,RClock);
input [5:0] Data;
output [5:0] Q;
input [10:0] WAddress, RAddress;
input WE, RE, WClock, RClock;

wire WEP, REP, VCC, GND;

VCC VCC_1_net(.Y(VCC));
GND GND_1_net(.Y(GND));
RAM64K36P ram_2048x6_R0C2(.WCLK(WClock), .RCLK(RClock),
  .DEPTH0(GND), .DEPTH1(GND), .DEPTH2(GND), .DEPTH3(GND),
  .WEN(WE), .WW0(VCC), .WW1(GND), .WW2(GND), .WRAD0(
  WAddress[0]), .WRAD1(WAddress[1]), .WRAD2(WAddress[2]),
  .WRAD3(WAddress[3]), .WRAD4(WAddress[4]), .WRAD5(
  WAddress[5]), .WRAD6(WAddress[6]), .WRAD7(WAddress[7]),
  .WRAD8(WAddress[8]), .WRAD9(WAddress[9]), .WRAD10(
  WAddress[10]), .WRAD11(GND), .WRAD12(GND), .WRAD13(GND),
  .WRAD14(GND), .WRAD15(GND), .WD0(Data[4]), .WD1(Data[5]),

```

```

.WD2(GND), .WD3(GND), .WD4(GND), .WD5(GND), .WD6(GND),
.WD7(GND), .WD8(GND), .WD9(GND), .WD10(GND), .WD11(GND),
.WD12(GND), .WD13(GND), .WD14(GND), .WD15(GND), .WD16(GND)
,.WD17(GND), .WD18(GND), .WD19(GND), .WD20(GND), .WD21(
GND), .WD22(GND), .WD23(GND), .WD24(GND), .WD25(GND),
.WD26(GND), .WD27(GND), .WD28(GND), .WD29(GND), .WD30(GND)
,.WD31(GND), .WD32(GND), .WD33(GND), .WD34(GND), .WD35(
GND), .REN(REP), .RW0(VCC), .RW1(GND), .RW2(GND), .RDAD0(
RAddress[0]), .RDAD1(RAddress[1]), .RDAD2(RAddress[2]),
.RDAD3(RAddress[3]), .RDAD4(RAddress[4]), .RDAD5(
RAddress[5]), .RDAD6(RAddress[6]), .RDAD7(RAddress[7]),
.RDAD8(RAddress[8]), .RDAD9(RAddress[9]), .RDAD10(
RAddress[10]), .RDAD11(GND), .RDAD12(GND), .RDAD13(GND),
.RDAD14(GND), .RDAD15(GND), .RD0(Q[4]), .RD1(Q[5]), .RD2(
.RD3(), .RD4(), .RD5(), .RD6(), .RD7(), .RD8(), .RD9(),
.RD10(), .RD11(), .RD12(), .RD13(), .RD14(), .RD15(),
.RD16(), .RD17(), .RD18(), .RD19(), .RD20(), .RD21(),
.RD22(), .RD23(), .RD24(), .RD25(), .RD26(), .RD27(),
.RD28(), .RD29(), .RD30(), .RD31(), .RD32(), .RD33(),
.RD34(), .RD35());
```

INV REBUBBLE(.A(RE), .Y(REP));

INV WEBUBBLE(.A(WE), .Y(WEP));

```

RAM64K36Pram_2048x6_R0C1(.WCLK(WClock), .RCLK(RClock),
.DEPTH0(GND), .DEPTH1(GND), .DEPTH2(GND), .DEPTH3(GND),
.WEN(WEP), .WW0(VCC), .WW1(GND), .WW2(GND), .WRAD0(
WAddress[0]), .WRAD1(WAddress[1]), .WRAD2(WAddress[2]),
.WRAD3(WAddress[3]), .WRAD4(WAddress[4]), .WRAD5(
WAddress[5]), .WRAD6(WAddress[6]), .WRAD7(WAddress[7]),
.WRAD8(WAddress[8]), .WRAD9(WAddress[9]), .WRAD10(
WAddress[10]), .WRAD11(GND), .WRAD12(GND), .WRAD13(GND),
.WRAD14(GND), .WRAD15(GND), .WD0(Data[2]), .WD1(Data[3]),
.WD2(GND), .WD3(GND), .WD4(GND), .WD5(GND), .WD6(GND),
.WD7(GND), .WD8(GND), .WD9(GND), .WD10(GND), .WD11(GND),
.WD12(GND), .WD13(GND), .WD14(GND), .WD15(GND), .WD16(GND)
,.WD17(GND), .WD18(GND), .WD19(GND), .WD20(GND), .WD21(
GND), .WD22(GND), .WD23(GND), .WD24(GND), .WD25(GND),
.WD26(GND), .WD27(GND), .WD28(GND), .WD29(GND), .WD30(GND)
,.WD31(GND), .WD32(GND), .WD33(GND), .WD34(GND), .WD35(
GND), .REN(REP), .RW0(VCC), .RW1(GND), .RW2(GND), .RDAD0(
RAddress[0]), .RDAD1(RAddress[1]), .RDAD2(RAddress[2]),
.RDAD3(RAddress[3]), .RDAD4(RAddress[4]), .RDAD5(
RAddress[5]), .RDAD6(RAddress[6]), .RDAD7(RAddress[7]),
.RDAD8(RAddress[8]), .RDAD9(RAddress[9]), .RDAD10(
RAddress[10]), .RDAD11(GND), .RDAD12(GND), .RDAD13(GND),
.RDAD14(GND), .RDAD15(GND), .RD0(Q[2]), .RD1(Q[3]), .RD2(
.RD3(), .RD4(), .RD5(), .RD6(), .RD7(), .RD8(), .RD9(),
.RD10(), .RD11(), .RD12(), .RD13(), .RD14(), .RD15(),
.RD16(), .RD17(), .RD18(), .RD19(), .RD20(), .RD21(),
.RD22(), .RD23(), .RD24(), .RD25(), .RD26(), .RD27(),
.RD28(), .RD29(), .RD30(), .RD31(), .RD32(), .RD33(),
.RD34(), .RD35());
```

```

RAM64K36Pram_2048x6_R0C0(.WCLK(WClock), .RCLK(RClock),
.DEPTH0(GND), .DEPTH1(GND), .DEPTH2(GND), .DEPTH3(GND),
.WEN(WEP), .WW0(VCC), .WW1(GND), .WW2(GND), .WRAD0(
WAddress[0]), .WRAD1(WAddress[1]), .WRAD2(WAddress[2]),
.WRAD3(WAddress[3]), .WRAD4(WAddress[4]), .WRAD5(
```

```

WAddress[5]), .WRAD6(WAddress[6]), .WRAD7(WAddress[7]),
.WRAD8(WAddress[8]), .WRAD9(WAddress[9]), .WRAD10(
WAddress[10]), .WRAD11(GND), .WRAD12(GND), .WRAD13(GND),
.WRAD14(GND), .WRAD15(GND), .WD0(Data[0]), .WD1(Data[1]),
.WD2(GND), .WD3(GND), .WD4(GND), .WD5(GND), .WD6(GND),
.WD7(GND), .WD8(GND), .WD9(GND), .WD10(GND), .WD11(GND),
.WD12(GND), .WD13(GND), .WD14(GND), .WD15(GND), .WD16(GND)
, .WD17(GND), .WD18(GND), .WD19(GND), .WD20(GND), .WD21(
GND), .WD22(GND), .WD23(GND), .WD24(GND), .WD25(GND),
.WD26(GND), .WD27(GND), .WD28(GND), .WD29(GND), .WD30(GND)
, .WD31(GND), .WD32(GND), .WD33(GND), .WD34(GND), .WD35(
GND), .REN(REP), .RW0(VCC), .RW1(GND), .RW2(GND), .RDAD0(
RAddress[0]), .RDAD1(RAddress[1]), .RDAD2(RAddress[2]),
.RDAD3(RAddress[3]), .RDAD4(RAddress[4]), .RDAD5(
RAddress[5]), .RDAD6(RAddress[6]), .RDAD7(RAddress[7]),
.RDAD8(RAddress[8]), .RDAD9(RAddress[9]), .RDAD10(
RAddress[10]), .RDAD11(GND), .RDAD12(GND), .RDAD13(GND),
.RDAD14(GND), .RDAD15(GND), .RD0(Q[0]), .RD1(Q[1]), .RD2(
, .RD3(), .RD4(), .RD5(), .RD6(), .RD7(), .RD8(), .RD9(),
.RD10(), .RD11(), .RD12(), .RD13(), .RD14(), .RD15(),
.RD16(), .RD17(), .RD18(), .RD19(), .RD20(), .RD21(),
.RD22(), .RD23(), .RD24(), .RD25(), .RD26(), .RD27(),
.RD28(), .RD29(), .RD30(), .RD31(), .RD32(), .RD33(),
.RD34(), .RD35());
```

endmodule

```

`timescale 1 ns/100ps
// Version: 6.2 SP2 6.2.52.7
```

```

module mux_6x4(Data0_port,Data1_port,Data2_port,Data3_port,Sel0,
  Sel1,Result);
  input [5:0] Data0_port, Data1_port, Data2_port, Data3_port;
  input Sel0, Sel1;
  output [5:0] Result;

  MX4 MX4_Result_0_inst(.D0(Data0_port[0]), .D1(Data1_port[0]),
    .D2(Data2_port[0]), .D3(Data3_port[0]), .S0(Sel0), .S1(
      Sel1), .Y(Result[0]));
  MX4 MX4_Result_2_inst(.D0(Data0_port[2]), .D1(Data1_port[2]),
    .D2(Data2_port[2]), .D3(Data3_port[2]), .S0(Sel0), .S1(
      Sel1), .Y(Result[2]));
  MX4 MX4_Result_5_inst(.D0(Data0_port[5]), .D1(Data1_port[5]),
    .D2(Data2_port[5]), .D3(Data3_port[5]), .S0(Sel0), .S1(
      Sel1), .Y(Result[5]));
  MX4 MX4_Result_1_inst(.D0(Data0_port[1]), .D1(Data1_port[1]),
    .D2(Data2_port[1]), .D3(Data3_port[1]), .S0(Sel0), .S1(
      Sel1), .Y(Result[1]));
  MX4 MX4_Result_4_inst(.D0(Data0_port[4]), .D1(Data1_port[4]),
    .D2(Data2_port[4]), .D3(Data3_port[4]), .S0(Sel0), .S1(
      Sel1), .Y(Result[4]));
  MX4 MX4_Result_3_inst(.D0(Data0_port[3]), .D1(Data1_port[3]),
    .D2(Data2_port[3]), .D3(Data3_port[3]), .S0(Sel0), .S1(
      Sel1), .Y(Result[3]));

endmodule
```




a  **MICROCHIP** company

Microsemi Headquarters
One Enterprise, Aliso Viejo,
CA 92656 USA
Within the USA: +1 (800) 713-4113
Outside the USA: +1 (949) 380-6100
Sales: +1 (949) 380-6136
Fax: +1 (949) 215-4996
Email: AVO-sales.support@microchip.com
www.microsemi.com

© 2015–2018 Microsemi. All rights reserved. Microsemi and the Microsemi logo are trademarks of Microsemi Corporation. All other trademarks and service marks are the property of their respective owners.

Microsemi makes no warranty, representation, or guarantee regarding the information contained herein or the suitability of its products and services for any particular purpose, nor does Microsemi assume any liability whatsoever arising out of the application or use of any product or circuit. The products sold hereunder and any other products sold by Microsemi have been subject to limited testing and should not be used in conjunction with mission-critical equipment or applications. Any performance specifications are believed to be reliable but are not verified, and Buyer must conduct and complete all performance and other testing of the products, alone and together with, or installed in, any end-products. Buyer shall not rely on any data and performance specifications or parameters provided by Microsemi. It is the Buyer's responsibility to independently determine suitability of any products and to test and verify the same. The information provided by Microsemi hereunder is provided "as-is, where is" and with all faults, and the entire risk associated with such information is entirely with the Buyer. Microsemi does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other IP rights, whether with regard to such information itself or anything described by such information. Information provided in this document is proprietary to Microsemi, and Microsemi reserves the right to make any changes to the information in this document or to any products and services at any time without notice.

Microsemi, a wholly owned subsidiary of Microchip Technology Inc. (Nasdaq: MCHP), offers a comprehensive portfolio of semiconductor and system solutions for aerospace & defense, communications, data center and industrial markets. Products include high-performance and radiation-hardened analog mixed-signal integrated circuits, FPGAs, SoCs and ASICs; power management products; timing and synchronization devices and precise time solutions; setting the world's standard for time; voice processing devices; RF solutions; discrete components; enterprise storage and communication solutions; security technologies and scalable anti-tamper products; Ethernet solutions; Power-over-Ethernet ICs and midspans; as well as custom design capabilities and services. Microsemi is headquartered in Aliso Viejo, California, and has approximately 4,800 employees globally. Learn more at www.microsemi.com.