AC341 Application Note CCGA to CLGA Adapter Socket





Power Matters.*

Microsemi Corporate Headquarters
One Enterprise, Aliso Viejo,
CA 92656 USA
Within the USA: +1 (800) 713-4113
Outside the USA: +1 (949) 380-6100
Fax: +1 (949) 215-4996
Email: sales.support@microsemi.com
www.microsemi.com

© 2016 Microsemi Corporation. All rights reserved. Microsemi and the Microsemi logo are trademarks of Microsemi Corporation. All other trademarks and service marks are the property of their respective owners.

Microsemi makes no warranty, representation, or guarantee regarding the information contained herein or the suitability of its products and services for any particular purpose, nor does Microsemi assume any liability whatsoever arising out of the application or use of any product or circuit. The products sold hereunder and any other products sold by Microsemi have been subject to limited testing and should not be used in conjunction with mission-critical equipment or applications. Any performance specifications are believed to be reliable but are not verified, and Buyer must conduct and complete all performance and other testing of the products, alone and together with, or installed in, any end-products. Buyer shall not rely on any data and performance specifications or parameters provided by Microsemi. It is the Buyer's responsibility to independently determine suitability of any products and to test and verify the same. The information provided by Microsemi hereunder is provided "as is, where is" and with all faults, and the entire risk associated with such information is entirely with the Buyer. Microsemi does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other IP rights, whether with regard to such information itself or anything described by such information. Information provided in this document is proprietary to Microsemi, and Microsemi reserves the right to make any changes to the information in this document or to any products and services at any time without notice.

About Microsemi

Microsemi Corporation (Nasdaq: MSCC) offers a comprehensive portfolio of semiconductor and system solutions for aerospace & defense, communications, data center and industrial markets. Products include high-performance and radiation-hardened analog mixed-signal integrated circuits, FPGAs, SoCs and ASICs; power management products; timing and synchronization devices and precise time solutions, setting the world's standard for time; voice processing devices; RF solutions; discrete components; enterprise storage and communication solutions, security technologies and scalable anti-tamper products; Ethernet solutions; Power-over-Ethernet ICs and midspans; as well as custom design capabilities and services. Microsemi is headquartered in Aliso Viejo, California, and has approximately 4,800 employees globally. Learn more at www.microsemi.com.



Contents

1	Revisi	on History
	1.1	Revision 3.0
	1.2	Revision 2.0
	1.3	Revision 1.0
	1.0	TOVISION 1.0
2	CCGA	to CLGA Adapter
	2.1	CG to LG Adapter Socket
	2.2	CG to LG Adapter Socket Assembly Procedure
		2.2.1 Step 1
		2.2.2 Step 2
		2.2.3 Step 3
		2.2.4 Step 4
		2.2.5 Step 5
		2.2.6 Step 6
	2.3	CG1272 to LG1272 Adapter Socket Outline
	2.4	Reflow Profile
	2.5	CCGA to LG1272 Adapter Pin Mapping List
	2.6	Prototyped Product, Adapter, and PCB Design Matrix



Figures

Figure 1	CG1272 to LG1272 Adapter Socket Parts	. 2
	CG1272 to LG1272 Ceramic Adapter Top View, Bottom View and Orientation	
•	Soldering Column Attachment to CG1272 to LG1272 Adapter	
Figure 4	Assembling Socket Housing to CG1272 to LG1272 Adapter	. 4
Figure 5	Reflowing Adapter to PCB	. 4
Figure 6	Placing Socket Interposer into Adapter Assembly	Ę
Figure 7	Placing LG1272 Package into Adapter Assembly	Ę
Figure 8	Placing and Tightening Socket Lid Using Eight Screws and Optional Alignment Pins	. (
Figure 9	CG1272 to LG1272 Adapter Socket Outline (unit: mm)	. 7
Figure 10	Sample Temperature Profile for I/R or Convection Reflow	. 8



Tables

Table 1	Adapter Socket Part Numbers	. 2
Table 2	CCGA to LG1272 Adapter Pin Mapping List	. 8
Table 3	Prototyped Device PCB Design Matrix	. 9



1 Revision History

The revision history describes the changes that were implemented in the document. The changes are listed by revision, starting with the most current publication.

1.1 **Revision 3.0**

In revision 3.0 of this document, a recommendation to use a torque limit screwdriver was added. For more information, see CG to LG Adapter Socket Assembly Procedure, page 3.

1.2 Revision 2.0

The following is a summary of the changes in revision 2.0 of this document.

- The figure title for Figure 1, page 2 (SAR 41789) was updated.
- "Support" section was updated.

1.3 **Revision 1.0**

The following is a summary of the changes in revision 1.0 of this document.

- In the "Introduction" section, the phrase "with error detection and correction (EDAC) protected" [static RAM] was deleted and replaced with "embedded."
- The following figures were replaced:
 - Figure 1, page 2
 - Figure 2, page 3
 - Figure 5, page 4
 - Figure 9, page 7



2 CCGA to CLGA Adapter

RTAXTM-S/SL is a designed-for-space, metal-to-metal antifuse FPGA family by Microsemi. It is a derivative of the Axcelerator[®] family with up to two million system gates. RTAX-S/SL FPGAs provide designers with nearly 500K ASIC gates and embedded static RAM.

Microsemi offers RTAX-S/SL devices in two package types: ceramic column grid array (CCGA or CG) and ceramic quad flat pack (CQFP or CQ). Microsemi has developed CQ to LG and CG to LG adapter sockets for designers to prototype RTAX-S/SL devices in both CCGA and CQFP packages. These adapter sockets use the ceramic land grid array (LGA) package as a prototyping vehicle.

This document provides information about assembling the CG to LG adapter socket.

2.1 CG to LG Adapter Socket

The CG to LG adapter socket has an LG configuration on the top and a CG configuration on the bottom. The adapter socket enables customers to use an LG package during prototyping, and then switch to an equivalent CG package for production. The following table lists the top and bottom ordering part numbers.


Table 1 • Adapter Socket Part Numbers

Adapter Socket	Ordering Part Numbers	Prototyped and Prototype Device
CG1272 to LG1272	SK-RT4K-KITTOP SK-RT4K-CG1272-KITBTM	For prototyping RTAX4000S/SL-CG1272 using RTAX4000S/SL-LG1272 package

The following figure shows the CG1272 to LG1272 adapter socket parts.

- The kit top (SK-RT4K-KITTOP) contains an interposer (3), a socket lid (4), and eight screws (5).
- The kit bottom (SK-RT4K-CG1272-KITBTM) contains a ceramic adapter (1)—a unique adapter for RTAX4000S/SL, socket housing (2), and eight screws (5).


Figure 1 • CG1272 to LG1272 Adapter Socket Parts





The following figure shows the top view, bottom view, and orientation of the RTAX4000S/SL CG1272 to LG1272 adapter.

Figure 2 • CG1272 to LG1272 Ceramic Adapter Top View, Bottom View and Orientation



2.2 CG to LG Adapter Socket Assembly Procedure

The socket housing and the ceramic adapter, along with eight screws are required for SK-RT4K-CG1272-KITBTM assembly, and the socket lid, socket interposer, and eight remaining screws are required for SK-RT4K-KITTOP assembly.


The following steps describe how to assemble the CG to LG adapter socket.

2.2.1 Step 1

Solder the column attachment to the ceramic adapter.

Note: Do not reflow the adapter to the circuit board until the housing has been attached.

Figure 3 • Soldering Column Attachment to CG1272 to LG1272 Adapter






2.2.2 Step 2

Assemble the socket housing onto the adapter using eight of the screws provided in the kit. It is recommended to use a torque limit screwdriver with the setting 1.3 to 2.0 lb-in.

Figure 4 • Assembling Socket Housing to CG1272 to LG1272 Adapter




2.2.3 Step 3

Reflow the adapter (with socket housing mounted on it) to the printed circuit board (PCB).

Note: Reflow profiles depend upon the size of the board and other components, so it is recommended to perform reflow process optimization for better results.

Figure 5 • Reflowing Adapter to PCB






2.2.4 Step 4

Place the socket interposer into the adapter.


Figure 6 • Placing Socket Interposer into Adapter Assembly



2.2.5 Step 5

Place the LG1272 package into the adapter.

Figure 7 • Placing LG1272 Package into Adapter Assembly






2.2.6 Step 6

Place the socket lid on the socket housing, and tighten it using the remaining eight screws. It is recommended to use a torque limit screwdriver with the setting 1.3 to 2.0 lb-in.

Figure 8 • Placing and Tightening Socket Lid Using Eight Screws and Optional Alignment Pins






2.3 CG1272 to LG1272 Adapter Socket Outline

The following figure shows the CG1272 to LG1272 adapter socket outline.

Figure 9 • CG1272 to LG1272 Adapter Socket Outline (unit: mm)






2.4 Reflow Profile

Since reflow profile depends upon the size of the board and other components, end users must perform additional fine tuning from the general profile shown in the following figure.

Figure 10 • Sample Temperature Profile for I/R or Convection Reflow



Note: This temperature profile guideline is for reference only.

2.5 CCGA to LG1272 Adapter Pin Mapping List

In the CG1272 to LG1272 adapter, each LG pad is routed to the corresponding CG pad. For example, LG1272 A1 is connected to CG1272 A1; LG1272 A2 is connected to CG1272 A2; and so on.

Table 2 • CCGA to LG1272 Adapter Pin Mapping List

Adapter Socket	Ordering Part Number	Prototyped and Prototype Device	Document Number
CG1272 to LG1272	SK-RT4K-KITTOP and	For prototyping RTAX4000S/SL-CG1272	N/A
	SK-RT4K-CG1272-KITBTM	using RTAX4000S/SL-LG1272 package	



2.6 Prototyped Product, Adapter, and PCB Design Matrix

Designing PCBs for specific products requires an understanding of which adapter socket works for specific products. Each adapter socket is routed differently based on the Axcelerator device (or radiation-tolerant equivalent derivative) being prototyped, and the commercial Axcelerator FG package used for prototyping. The following table lists the device-PCB combinations that work.

Table 3 • Prototyped Device PCB Design Matrix

Prototyped Product	Adapter Part Number	Prototyping Vehicle	PCB Design
RTAX4000S/SL-CG1272	SK-RT4K-KITTOP and SK-RT4K-CG1272-KITBTM	RTAX4000S/SL-LG1272	RTAX4000S/SL-CG1272