ZL4029x

Perfect Timing – Meet Your DB2000 Requirements Today With Microchip's Ultra-Low Jitter, Low-Power Buffers

Summary

The ZL4029x are a family of high-performance, ultra-low jitter, low power 1 to 20 HCSL fanout buffers. The ZL40292 and ZL40294 are fully compliant to the DB2000Q and DB2000QL standard while the ZL40293 and ZL40295 can be used in PCIe Gen 1 through 5 applications requiring a 100 ohm termination. Applications include PCI Express generation 1/2/3/4/5 clock distribution, Intel QPI servers, storage and data centers, switches and routers.



Key Attributes

- Fully compliant with Intel DB2000Q and DB2000QL specification
- 20 low-power push-pull HCSL PCIe outputs
- Ultra-low additive jitter: 15 fs typical
- Supports clock frequencies from 0 to 250 MHz
- Supports 3.3V power supplies
- Embedded Low Drop Out (LDO) voltage regulator provides superior power supply noise rejection
- Maximum output to output skew of 40 ps
- SMBus interface
- Eight OE pins
- Transparent for spread-spectrum clock

Target Applications

- PCI Express generation 1/2/3/4/5
- Clock distribution
- Intel QPI servers
- Storage and data centers
- Switches and routers



Product Variants

Part Number	Output Frequencies (MHz)	Number of Outputs	Standard	Termination	Jitter (max RMS)	Interfaces	Package	Media
ZL40292 LDG1	Up to 250	20	DB2000Q PCle Gen 1-5	85Ω	20 fs	8 OE pins+SMBus	72-pin 10 × 10 QFN	Tray
ZL40292 LDF1	Up to 250	20	DB2000Q PCle Gen 1-5	85Ω	20 fs	8 OE pins+SMBus	72-pin 10 × 10 QFN	T/R
ZL40293 LDG1	Up to 250	20	PCle Gen 1-5	100Ω	20 fs	8 OE pins+SMBus	72-pin 10 × 10 QFN	Tray
ZL40293 LDF1	Up to 250	20	PCle Gen 1-5	100Ω	20 fs	8 OE pins+SMBus	72-pin 10 × 10 QFN	T/R
ZL40294 LDG1	Up to 250	20	DB2000QL PCle Gen 1-5	85Ω	20 fs	8 OE pins+SMBus+SBI	80-pin 6 × 6 GQFN	Tray
ZL40294 LDF1	Up to 250	20	DB2000QL PCle Gen 1-5	85Ω	20 fs	8 OE pins+SMBus+SBI	80-pin 6 × 6 GQFN	T/R
ZL40295 LDG1	Up to 250	20	PCle Gen 1-5	100Ω	20 fs	8 OE pins+SMBus+SBI	80-pin 6 × 6 GQFN	Tray
ZL40295 LDF1	Up to 250	20	PCle Gen 1-5	100Ω	20 fs	8 OE pins+SMBus+SBI	80-pin 6 × 6 GQFN	T/R

https://www.microsemi.com/product-directory/clock-fan-out-buffers/5516-zl40292-zl40293#overview

More Clock and Timing products From The Industry's Broadest Timing Portfolio



Oscillators MEMS | Crystal | OCXO | EMXO

TCXO | MCXO | VCXO | VCSO

Jitter Attenuation

Jitter filtering | Clock translation Any in/any out | Internal EEPROM Advanced DPLL





Clock Generation

Clock Distribution

Dividers | Multiplexers

Low jitter | Low power Any in/any out | Clock tree on a chip Integrated MEMS/Xtal resonator

Low additive Jitter | Any In/Any Out

Fanout buffers | Zero-delay buffers

Synchronization

Synchronous Ethernet | IEEE1588 Servo algorithm OTN/GPS PLLS Firmware and software support

Complimentary

Logic translators | Cross point switches Backplane and cable | Skew management Flip-flop/logic gates



The Microchip name and logo and the Microchip logo are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries. All other trademarks mentioned herein are property of their respective companie © 2019, Microchip Technology Incorporated. All Rights Reserved. 6/19

DS00003013B



www.microchip.com/timing