

# IEEE 1588 Selector Guide

## Line Card/Transport Interface

Part No.	Description	BW (Hz)	Inputs	Input Frequency	Diff. Outputs	CMOS Outputs	Output Frequency	Low-Jitter APLLs	GP Clock Gen	Jitter (pSRMS)	Pkg size (mm)
ZL30347	Single Ch 1588-SyncE DPLL - 1GbE	0.5m-400	2 D/SE	N x 8K, SyncE	2	6	N x 8K, SDH, SyncE	1-Int-N	2	1.0	9 x 9
ZL30365	Quad channel combined IEEE 1588 ToP and SyncE device	5-890	8 D/SE	1 Hz-750 MHz	8	8	1 Hz-750 MHz	4	0	0.65	13 x 13
ZL30367	Dual channel combined IEEE 1588 ToP and SyncE device	5-890	9 D/SE+2 SE	1 Hz-750 MHz	6	6	1 Hz-750 MHz	3	0	0.65	13 x 13

## Timing Card/System Controller/Single Board/SETS with Transport Interface

Part No.	Description	DPLLs	BW (Hz)	Inputs	Input Frequency	Embedded PPS & EPP2S	Diff. Out-puts	CMOS Out-puts	Output Frequency	Low-Jitter APLLs	GP Clock Gen	Jitter (pSRMS)	Pkg size (mm)
ZL30342	Single Ch 1588-SyncE DPLL - 1GbE	1 NCO	0.1-890	3 SE	N x 8K, SyncE		1	2	N x 8K, SDH, SyncE	1-Int-N	1	1.0	9 x 9
ZL30343	Dual Ch 1588-SyncE DPLL - 1GbE	2 NCO	0.1-890	8 SE	N x 8K, SyncE		2	6	N x 8K, SDH, SyncE	1-Int-N	2	1.0	9 x 9
ZL30361	Any-Freq. Single Ch 1588-SyncE PLL/NCO - 1GbE/10GbE	1 NCO	0.1-896	11	1 Hz-750 MHz		6	6	1 Hz-750 MHz	3	0	0.65	13 x 13
ZL30362	Any-Freq. Quad Ch 1599-SyncE PLL/NCO - 1GbE/10GbE	4 NCO	0.1-896	11	1 Hz-750 MHz		8	8	1 Hz-750 MHz	4	0	0.65	13 x 13
ZL30363	Any-Freq. Dual Ch 1588-SyncE PLL/NCO - 1GbE/10GbE	2 NCO	0.1-896	11	1 Hz-750 MHz		8	8	1 Hz-750 MHz	4	0	0.65	13 x 13
ZL30364	Any-Freq. Triple Ch 1588-SyncE PLL/NCO - 1GbE/10GbE	3 NCO	0.1-896	11	1 Hz-750 MHz		8	8	1 Hz-750 MHz	4	0	0.65	13 x 13
ZL30721	Single Ch 1588-SyncE PLL/NCO Small Footprint - 10GbE *	1 NCO	0.1-10	2 D/SE + 1 SE	8 kHz-1250 MHz		3	6	<1 Hz-1035 MHz	1	0	0.25	5 x 10
ZL30722	Single Ch 1588-SyncE PLL/NCO Small Footprint - 10GbE	1 NCO	0.1-500	2 D/SE + 1 SE	8 kHz-1250 MHz		3	6	<1 Hz-1035 MHz	1	0	0.25	5 x 5
ZL30723	Dual Ch 1588-SyncE PLL/NCO Small Footprint - 10GbE	2 NCO	0.1-500	4 D/SE + 1 SE	8 kHz-1250 MHz		6	12	<1 Hz-1035 MHz	2	0	0.25	5 x 10
ZL30701	Any-Freq. Single Ch 1588-SyncE PLL/NCO - 10GbE/40GbE/100GbE	1 or (1 NCO)	0.1m- 470	5 D/10 SE	0.5 Hz-900 MHz	•	6	14	0.5 Hz-900 MHz	2 or 3	1	0.18	10 x 10
ZL30702	Any-Freq. Dual Ch 1588-SyncE PLL/NCO - 10GbE/40GbE/100GbE	2 or (2 NCO)	0.1m- 470	5 D/10 SE	0.5 Hz-900 MHz	•	6	14	0.5 Hz-900 MHz	2 or 3	1	0.18	10 x 10
ZL30703	Any-Freq. Triple Ch 1588-SyncE PLL/NCO - 10GbE/40GbE/100GbE	3 or (3 NCO)	0.1m- 470	5 D/10 SE	0.5 Hz-900 MHz	•	6	14	0.5 Hz-900 MHz	2 or 3	1	0.18	10 x 10
ZL30704	Any-Freq. Quad Ch 1588-SyncE PLL/NCO - 10GbE/40GbE/100GbE	4 or (4 NCO)	0.1m- 470	5 D/10 SE	0.5 Hz-900 MHz	•	6	14	0.5 Hz-900 MHz	2 or 3	1	0.18	10 x 10

\* Low-jitter operation from any 10MHz TCXO

### Abbreviations:

D= Differential, SE= Single-ended, GP= General purpose, NCO= Numerically controlled oscillator, ToP= Timing over packet, SyncE= Synchronous Ethernet, SS= SONET/SDH, FC= Frequency conversion/T4 DPLL.

Microsemi is continually adding new products to its industry-leading portfolio.

For the most recent updates to our product line and for detailed information and specifications, please call, email or visit our website:

**Toll-free: 800-713-4113**

**[sales.support@microsemi.com](mailto:sales.support@microsemi.com)**

**[www.microsemi.com](http://www.microsemi.com)**



**Microsemi Corporate Headquarters**  
One Enterprise, Aliso Viejo, CA 92656 USA  
Within the USA: +1 (800) 713-4113  
Outside the USA: +1 (949) 380-6100  
Fax: +1 (949) 215-4996  
Email: [sales.support@microsemi.com](mailto:sales.support@microsemi.com)  
[www.microsemi.com](http://www.microsemi.com)

Microsemi Corporation (Nasdaq: MSCC) offers a comprehensive portfolio of semiconductor and system solutions for aerospace & defense, communications, data center and industrial markets. Products include high-performance and radiation-hardened analog mixed-signal integrated circuits, FPGAs, SoCs and ASICs; power management products; timing and synchronization devices and precise time solutions, setting the world's standard for time; voice processing devices; RF solutions; discrete components; enterprise storage and communication solutions, security technologies and scalable anti-tamper products; Ethernet solutions; Power-over-Ethernet ICs and midspans; as well as custom design capabilities and services. Microsemi is headquartered in Aliso Viejo, California and has approximately 4,800 employees globally. Learn more at [www.microsemi.com](http://www.microsemi.com).

Microsemi makes no warranty, representation, or guarantee regarding the information contained herein or the suitability of its products and services for any particular purpose, nor does Microsemi assume any liability whatsoever arising out of the application or use of any product or circuit. The products sold hereunder and any other products sold by Microsemi have been subject to limited testing and should not be used in conjunction with mission-critical equipment or applications. Any performance specifications are believed to be reliable but are not verified, and Buyer must conduct and complete all performance and other testing of the products, alone and together with, or installed in, any end-products. Buyer shall not rely on any data and performance specifications or parameters provided by Microsemi. It is the Buyer's responsibility to independently determine suitability of any products and to test and verify the same. The information provided by Microsemi hereunder is provided "as is, where is" and with all faults, and the entire risk associated with such information is entirely with the Buyer. Microsemi does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other IP rights, whether with regard to such information itself or anything described by such information. Information provided in this document is proprietary to Microsemi, and Microsemi reserves the right to make any changes to the information in this document or to any products and services at any time without notice.

©2016 Microsemi Corporation. All rights reserved. Microsemi and the Microsemi logo are registered trademarks of Microsemi Corporation. All other trademarks and service marks are the property of their respective owners.